

Signal conditioner - MINI MCR-SL-UI-UI - 2864383

Please be informed that the data shown in this PDF Document is generated from our Online Catalog. Please find the complete data in the user's documentation. Our General Terms of Use for Downloads are valid (<http://phoenixcontact.com/download>)



MCR 3-way signal conditioner, input/output can be configured via DIP switches, for the electrical isolation of analog signals, with screw connection, order configuration. Replacement part: 2902036 MINI MCR-2-UI-UI-C.

Product Description

The 6.2 mm wide configurable 3-way isolating amplifier MINI MCR-SL-UI-UI-... is used for electrical isolation, conversion, amplification and filtering of standard signals.

The standard signals 0...20 mA, 4...20 mA, 0...10 V, 2...10 V, 0...5 V or 1...5V are available electrically isolated on the input and output side.

The DIP switches, which can be accessed on the side of the housing, can be used to configure the input and output signal ranges.

Power (19.2 V DC to 30 V DC) can be supplied through connection terminal blocks on the modules or in conjunction with the DIN rail connector.

Your advantages

- ✓ Power supply possible via the foot element (TBUS)
- ✓ Up to 36 signal combinations can be configured using DIP switches
- ✓ Low power consumption
- ✓ Highly-compact isolating amplifier for electrical isolation, conversion, amplification, and filtering of standard analog signals
- ✓ 3-way isolation



Key Commercial Data

Packing unit	1 pc
Weight per Piece (excluding packing)	80.000 g
Custom tariff number	85437090
Country of origin	Germany