

withdraw. non-aut. circuit-b. with guide frame 4-pole, size III, IEC In=4000A to 690V, AC50/60Hz Icu=100kA at 500V rear connection horizontal without overcurrent release
Motorized/manual operating mechanism with spring charging motor AC 50/60 Hz 208-240 V or 220-250 V DC Activation AC 50/60 Hz 230 V, 220 V DC With 1st auxiliary release Shunt release "F", F1 50/60 Hz 230 V AC/220 V DC, 100% on-load factor With 2nd auxiliary release "R", F3 Undervoltage, instant. 208-240 V AC, 220-250 V DC 4NO+4NC C01= Mechanical switching cycle counter C22= Ready-to-close signaling K07= Caution!!! Order code K07 with non-automatic circuit breaker not possible!!! R16= Position signaling switch, withdrawable part 6 changeover contacts R21= Shutter 2-part can be locked with bracket lock

Further information

Industry Online Support (Manuals, Catalogs, Certificates, FAQ, ...)
<https://support.industry.siemens.com/cs/products?mf=ps&lc=en-WW>
Industry Mall (Online ordering system)
<https://mall.industry.siemens.com>

