



### Main

|  |  |
|--|--|
| Range  | TeSys  |
| Product name                                 | TeSys LE   |
| Device short name                            | LE2D   |
| Product or component type                    | Enclosed DOL reversing starter   |
| Device application                           | Standard   |
| Utilisation category                         | AC-3   |
| Device composition                           | Reversing contactor<br>Thermal overload relay to be ordered separately   |
| [Ie] rated operational current               | 50 A AC-3  |
| Motor power kW                               | 33 kW at 660/690 V AC 50/60 Hz<br>30 kW at 500 V AC 50/60 Hz<br>30 kW at 440 V AC 50/60 Hz<br>25 kW at 415 V AC 50/60 Hz<br>22 kW at 380/400 V AC 50/60 Hz<br>15 kW at 220/230 V AC 50/60 Hz |
| [Ithe] conventional enclosed thermal current | 50 A   |
| [Uc] control circuit voltage                 | 380 V AC 50/60 Hz  |
| Control type                                 | Selector switch 2 positions start I-II<br>Push-button stop/reset red O   |

### Complementary

|                    |   |
|--------------------|---|
| Cable entry number | 3 cable entry :1 ISO20 + 2 ISO32 bottom<br>1 cable entry :ISO32 top |
| Width              | 200 mm  |
| Height             | 300 mm  |
| Depth              | 174 mm  |
| Product weight     | 5.47 kg   |

### Environment

|                                       |                              |
|---------------------------------------|------------------------------|
| Material                              | Sheet steel                  |
| IP degree of protection               | IP65 conforming to IEC 60529 |
| IK degree of protection               | IK09 conforming to IEC 60529 |
| Standards                             | IEC 60947-4-1                |
| Ambient air temperature for operation | -5...40 °C                   |

The information provided in this documentation contains general descriptions and/or technical characteristics of the performance of the products contained herein. This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications. It is the duty of any such user or integrator to perform the appropriate and complete risk analysis, evaluation and testing of the products with respect to the relevant specific application or use thereof. Neither Schneider Electric Industries SAS nor any of its affiliates or subsidiaries shall be responsible or liable for misuse of the information contained herein.