



Main

| | |
|---------------------------------------|---------------------------|
| Range compatibility | Lexium 32 |
| Accessory / separate part category | Communication accessories |
| Accessory / separate part type | Module |
| Product or component type | Additional I/O module |
| Product compatibility | Lexium 32M |
| Accessory / separate part destination | Servo drive |

Complementary

| | |
|-----------------------------|----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| Input/Output type | 2 analog outputs : - 10...10 V, 0 A...20 mA, , 470 Ohm, resolution: 12 bits for 0.25 ms 2 analog inputs : - 10...10 V, , 20 kOhm, resolution: 14 bits for 0.25 ms 4 discrete inputs : - 3...5 V/15...30 V, 2.5 mA, for 0.25 ms 2 discrete outputs : <= 30 V, <= 100 mA, for 0.25 ms |
| Protection type | Reverse polarity protection on input |
| Reverse polarity protection | Yes on input |
| Short-circuit protection | Yes on output |
| Electrical connection | Spring terminal |
| Product weight | 0.45 kg |

Offer Sustainability

| | |
|----------------------------------|---------------------------------------------------------------------------------------|
| Sustainable offer status | Green Premium product |
| RoHS (date code: YYWW) | Compliant - since 1401 - Schneider Electric declaration of conformity |
| REACH | Reference not containing SVHC above the threshold |
| Product environmental profile | Available Download Product Environmental |
| Product end of life instructions | Available Download End Of Life Manual |

The information provided in this documentation contains general descriptions and/or technical characteristics of the performance of the products contained herein. This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications. It is the duty of any such user or integrator to perform the appropriate and complete risk analysis, evaluation and testing of the products with respect to the relevant specific application or use thereof. Neither Schneider Electric Industries SAS nor any of its affiliates or subsidiaries shall be responsible or liable for misuse of the information contained herein.