

Data sheet for three-phase Squirrel-Cage-Motors INNOMOTICS



Motor type : 1AV3131A

INNOMOTICS GP - 132 S - IM V1 - 2p

Client order no.	Item-No.	Offer no.
Order no.	Consignment no.	Project

Remarks	Safe Area
	-/-

U	Δ / Y	f	P	P	I	n	M	η ³⁾			cosφ ³⁾			I _A /I _N	M _A /M _N	M _K /M _N	IE-CL
[V]		[Hz]	[kW]	[hp]	[A]	[1/min]	[Nm]	4/4	3/4	2/4	4/4	3/4	2/4	I _I /I _N	T _I /T _N	T _B /T _N	
DOL duty (S1) - 155(F) to 130(B)																	
400	Δ	50	7.50	-/-	13.10	2950	24.5	90.1	90.9	90.7	0.92	0.89	0.84	8.3	2.1	4.0	IE3
460	Δ	60	8.60	-/-	13.00	3550	23.0	90.2	90.5	90.0	0.92	0.91	0.85	8.4	2.1	4.1	IE3
460	Δ	60	7.50	10.00	11.50	3555	20.0	90.2	90.5	90.0	0.91	0.90	0.84	9.5	2.4	4.7	MG1
IM V1 / IM 3011		FS 132 S		CC032A		IP55	UKCA	IEC/EN 60034		IEC, EN, UL, CSA, NEMA MG1-12-12				kVA Code: M			
Environmental conditions : -20 °C - +40 °C / 1000 m									Locked rotor time (hot / cold) : 12.7 s 17.3 s								

Mechanical data				
Sound level (SPL / SWL) at 50Hz 60Hz	68 / 80 dB(A) ^{2) 3)}	72 / 84 dB(A) ^{2) 3)}	Vibration severity grade	A
Moment of inertia	0.0310 kg m²		Thermal class	F
Bearing DE NDE	6208 2Z C3	6208 2Z C3	Duty type	S1
bearing lifetime			Direction of rotation	bidirectional
L _{10mh} F _{Rad min} for coupling operation 50 60Hz ¹⁾	20000 h	16000 h	Frame material	aluminum
Regreasing device	Without		Net weight of the motor (IM B3)	57 kg
Grease nipple	-/-		Coating (paint finish)	Standard paint finish C2
Type of bearing	Locating bearing DE		Color, paint shade	RAL7030
Condensate drainage holes	Without		Motor protection	(B) 3 PTC thermistors - for tripping (2 terminals)
External earthing terminal	Without		Method of cooling	IC411 - self ventilated, surface cooled

Terminal box																	
Terminal box position			top			Max. cross-sectional area			6 mm²								
Material of terminal box			Aluminium			Cable diameter from ... to ...			11 mm - 21 mm								
Type of terminal box			TB1 H00			Cable entry			2xM32x1,5-1xM16x1,5								
Contact screw thread			M4			Cable gland			3 plugs								

I_A/I_N = locked rotor current / current nominal
M_K/M_N = locked rotor torque / torque nominal
M_B/M_N = break down torque / nominal torque

1) L_{10mh} according to DIN ISO 281 10/2010
2) at rated power I at full load

3) Value is valid only for DOL operation with motor design IC411

Transmittal, reproduction, dissemination and/or editing of this document as well as utilization of its contents and communication thereof to others without express authorization are prohibited. Offenders will be held liable for payment of damages. All rights created by patent grant or registration of a utility model or design patent are reserved.

Responsible department IN LVM	Technical reference	Created by SPC	Approved by Created automatically	Technical data are subject to change! There may be discrepancies between calculated and rating plate values.	Link documents
INNOMOTICS	Document type Technical data sheet			Document status Released	
	Document title 1LE1023-1CA13-4GB4-Z L20			Document number TDS-240905-131203	
Restricted © Innomotics 2024				Revision AA	Creation date 2024-09-05
			Language en	Page 1/2	

Data sheet for three-phase Squirrel-Cage-Motors INNOMOTICS



Motor type : 1AV3131A

INNOMOTICS GP - 132 S - IM V1 - 2p

Special design

L20 Locating bearing, DE

Transmittal, reproduction, dissemination and/or editing of this document as well as utilization of its contents and communication thereof to others without express authorization are prohibited. Offenders will be held liable for payment of damages. All rights created by patent grant or registration of a utility model or design patent are reserved.

Responsible department IN LVM	Technical reference	Created by SPC	Approved by Created automatically	Technical data are subject to change! There may be discrepancies between calculated and rating plate values.		Link documents	
	Document type Technical data sheet			Document status Released			
	Document title 1LE1023-1CA13-4GB4-Z			Document number TDS-240905-131203			
	L20			Revision AA	Creation date 2024-09-05		
Restricted © Innomotics 2024						Language en	Page 2/2