

PRODUCT-DETAILS

MS132-10B

MS132-10B Manual Motor Starter



Ogólne informacje

Extended Product Type	MS132-10B
ID Produktu	1SAM350200R1010
Numer EAN	4013614521409
Opis katalogowy	MS132-10B Manual Motor Starter

Opis

MS132-B is a compact and powerful range for motor protection up to 15 kW (400 V) / 32 A in width of 45 mm, complying with the latest railway rolling stock standards and allowing installation in passengers or driver cabins for trains frequently operating tunnels or undergrounds.

They offer a reliable protection for motors in the event of overload or phase failure. The devices have trip class 10.

This type has also a clear and reliable indication of fault in a separate window in the event of short-circuit tripping. Further features are the build-in disconnect function, temperature compensation, trip-free mechanism and a rotary handle with a clear switch position indication. The manual motor starter is suitable for three- and single phase applications. The handle is lockable to protect against unauthorized changes.

Auxiliary contacts, signaling contacts, undervoltage releases, shunt trips, power in-feed blocks are available as accessory. These are suitable throughout the MS132-B/MS165-B range.

- designed in accordance to the applicable parts of IEC 60077 standard
- shocks and vibration withstand conforming to IEC 61373 (category 1, class B)
- usable according to European fire and smoke safety standard EN 45545-2

Charakterystyka zamówienia

Minimalna ilość zamówienia	1 sztuka
Kod taryfy celnej	85362010

Najczęściej Pobierane

Arkusz danych, informacja techniczna	1SBC100200C02__
Instrukcje i podręczniki	2CDC131022M6802
Instructions and Manuals (Part 2)	2CDC131060M0202
Time-Current Characteristic Curve	1SAM300505F0110

Wymiary

Szerokość produktu netto	45 mm
Wysokość produktu netto	90 mm
Głębokość produktu netto	86.75 mm
Waga produktu netto	0.265 kg

Dane techniczne

Rated Service Short-Circuit Breaking Capacity (I_{cs})	(230 V AC) 100 kA (250 V DC) 3 Poles in Series 10 kA (400 V AC) 100 kA (440 V AC) 30 kA (500 V AC) 20 kA (690 V AC) 3 kA
Rated Ultimate Short-Circuit Breaking Capacity (I_{cu})	(230 V AC) 100 kA (400 V AC) 100 kA (440 V AC) 30 kA (500 V AC) 20 kA (690 V AC) 3 kA
Rated Instantaneous Short-Circuit Current Setting (I_l)	150 A
Setting Range	6.3 ... 10 A
Moc znamionowa AC-3 (P_e)	(400 V) Three Phase 4 kW
Moc znamionowa AC-3e (P_e)	(400 V) Three Phase 4 kW
Znamionowe napięcie pracy	Obwód główny 690 V AC Obwód główny 250 V DC
Znamionowy prąd pracy (I_e)	10 A
Znamionowy prąd pracy AC-3 (I_e)	10 A
Znamionowy prąd pracy AC-3e (I_e)	10 A
Znamionowy prąd pracy DC-5 (I_e)	10 A
Częstotliwość	Obwód główny 50 Hz

znamionowa (f)	Obwód główny 60 Hz
Znamionowa wytrzymałość na impuls napięciowy (U_{imp})	Obwód główny 6 kV
Znamionowe napięcie izolacji (U_i)	690 V
Straty mocy	na biegun 0.8 W
Liczba biegunów	3
Prąd przy chłodzeniu konwencjonalnym (I_{th})	Obwód główny 10 A
Stopień ochrony obudowy	Housing IP20 Main Circuit Terminals IP10
Stopień zanieczyszczenia	3
Electrical Durability	50000 cycle
Wytrzymałość mechaniczna	100000 cycle
Typ terminala	Screw Terminals
Dane montażowe-obwód główny (roboczy)	Elastyczny z tulejką 1/2x 0.75 ... 2.5 mm ² Elastyczny z izolowaną tulejką 1/2x 0.75 ... 2.5 mm ² Elastyczny 1/2x 0.75 ... 2.5 mm ² Sztwiny 1/2x 1 ... 4 mm ²
Momenty dokrecające	Obwód główny (roboczy) 0.8 ... 1.2 N·m
Długość odizolowania przewodu	Obwód główny 9 mm
Recommended Screw Driver	Pozidriv 2
Pozycja montażu	Position 1 to 6
Montaż na szynie DIN	TH35-15 (Szyna montażowa 35 x 15 mm) wg IEC 60715 TH35-7.5 (Szyna montażowa 35 x 7.5 mm) wg IEC 60715
Minimum Mounting Distance	Electrical Conductive Board, Horizontal - Up to 400 V 0 mm Electrical Conductive Board, Horizontal - Up to 690 V 1.5 mm Electrical Conductive Board, Vertical 75 mm Other Device Same Type, Horizontal 0 mm Other Device Same Type, Vertical 150 mm
Typ napędu	Rotary Handle
Contact Position Indication	ON / OFF / TRIP
Standardy	IEC 60077-1 (applicable parts) IEC 60077-2 (applicable parts) IEC/EN 60947-1 IEC/EN 60947-2 IEC/EN 60947-4-1
Remarks	UL508 Self-Protected Combination Motor Controller (Type E) in combination with feeder block S1-M3-xx

Technical UL/CSA

Short-Circuit Current Rating (SCCR)	Manual Self-Protected Combination Controllers (Type E), (480Y / 277 V AC) 65 kA Manual Self-Protected Combination Controllers (Type E), (600Y / 347 V AC) 18 kA Any UL Listed Fuses or Circuit-Breakers, Group Installations (480 V AC) 65 kA Any UL Listed Fuses or Circuit-Breakers, Group Installations (600 V AC) 35 kA Any UL Listed Fuses or Circuit-Breakers, Motor Disconnect (480 V AC) 65 kA Any UL Listed Fuses or Circuit-Breakers, Motor Disconnect (600 V AC) 18 kA Any UL Listed Fuses or Circuit-Breakers, Tap Conductor Protection in Group Installations (480Y / 277 V AC) 65 kA Any UL Listed Fuses or Circuit-Breakers, Tap Conductor Protection in Group
-------------------------------------	--

	Installations (600Y / 347 V AC) 18 kA
Maksymalne napięcie robocze UL/CSA	Obwód główny 600 V AC
Napięcie znamionowe UL/CSA	10 A
Moc znamionowa [Hp] UL/CSA	200V AC Trzy fazy 2 Hp 208V AC Trzy fazy 2 Hp 220 ... 240V AC Trzy fazy 3 Hp 440 ... 480V AC Trzy fazy 5 Hp 550 ... 600V AC Trzy fazy 7.5 Hp
Full Load Amps Motor Use	200V AC Trzy fazy 7.8 A 208V AC Trzy fazy 7.5 A 220 ... 240V AC Trzy fazy 9.6 A 440 ... 480V AC Trzy fazy 7.6 A 550 ... 600V AC Trzy fazy 9 A
Locked Rotor Amps	200V AC Trzy fazy 57.5 A 208V AC Trzy fazy 55 A 220 ... 240V AC Trzy fazy 64 A 440 ... 480V AC Trzy fazy 46 A 550 ... 600V AC Trzy fazy 50.8 A
Znamionowe dane montażowe UL/CSA	(600 V AC) 10 A
Dane montażowe-obwód główny (roboczy) UL/CSA	Elastyczny 1/2x 16-12 AWG Skrętka 1/2x 16-12 AWG
Momenty dokrecające UL/CSA	Obwód główny (roboczy) 10 ... 12 in-lb

Normy środowiskowe

Temperatura powietrza otoczenia	Wokół obudowy 0 ... +40 °C Eksploatacja -25 ... +70 °C Eksploatacja zrównoważona -25 ... +60 °C Przechowywanie -50 ... +80 °C
Kompensacja temperatury powietrza otoczenia	Tak
Maksymalna wysokość montażu m.n.p.m	2000 m
Odporność na wstrząsy IEC 60068-2-27	11 ms Pulse 25g
Odporność na wibracje IEC 60068-2-6	5g / 3 ... 150 Hz
Status RoHS	Following EU Directive 2011/65/EU

Certyfikaty i deklaracje (Numer dokumentu)

Certyfikat CB	1SAA963002-2002
Certyfikat CQC	CQC2010010307387700
cUL Certificate	cUL_E137861 cUL_E345003
cULus Certificate	cUL_E137861
Declaration of Conformity - CCC	2020980307003526
Deklaracja zgodności - CE	1SAD938506-0197
Informacje środowiskowe	1SAC200050H0009
Instrukcje i podręczniki	2CDC131022M6802
Instructions and Manuals	2CDC131060M0202

(Part 2)

KC Certificate	1SAA963002-1502
Dane RoHS	1SAD938501-0197
Time-Current Characteristic Curve	1SAM300505F0110
UL Certificate	UL_E137861 UL_E345003

Informacje o pakowaniu

Jednostka opakowania (poziom 1)	box 1 sztuka
Szerokość opakowania (poziom 1)	92 mm
Długość opakowania (poziom 1)	95 mm
Wysokość opakowania (poziom 1)	50 mm
Waga opakowania brutto (poziom 1)	0.28 kg
EAN opakowania (poziom 1)	4013614521409
Jednostka opakowania (poziom 2)	carton 40 sztuka
Szerokość opakowania (poziom 2)	280 mm
Długość opakowania (poziom 2)	395 mm
Wysokość opakowania (poziom 2)	210 mm
Waga opakowania brutto (poziom 2)	14.026 kg
EAN opakowania (poziom 2)	4013614522994

Klasyfikacje

Kod klasyfikacji	F
ETIM 5	EC000074 - Motor protective circuit-breaker
ETIM 6	EC000074 - Motor protection circuit-breaker
ETIM 7	EC000074 - Motor protection circuit-breaker
eClass	V11.0 : 27370401
UNSPSC	39121521
IDEA Granular Category Code (IGCC)	4845 >> 3 Pole Motor Circuit Protector Circuit Breakers

Accessories

Identifier	Description	Type	Quantity	Unit Of Measure
1SAM201901R1001	HKF1-11 Auxiliary Contact	HKF1-11	1	piece
1SAM201901R1201	HKF1-11K Auxiliary Contact	HKF1-11K	1	piece

1SAM201901R1002	HKF1-20 Auxiliary Contact	HKF1-20	1	piece
1SAM201901R1202	HKF1-20K Auxiliary Contact	HKF1-20K	1	piece
1SAM201901R1004	HKF1-01 Auxiliary Contact	HKF1-01	1	piece
1SAM201901R1003	HKF1-10 Auxiliary Contact	HKF1-10	1	piece
1SAM201902R1002	HK1-20 Auxiliary Contact	HK1-20	1	piece
1SAM201902R1202	HK1-20K Auxiliary Contact	HK1-20K	1	piece
1SAM201902R1001	HK1-11 Auxiliary Contact	HK1-11	1	piece
1SAM201902R1201	HK1-11K Auxiliary Contact	HK1-11K	1	piece
1SAM201902R1003	HK1-02 Auxiliary Contact	HK1-02	1	piece
1SAM201902R1203	HK1-02K Auxiliary Contact	HK1-02K	1	piece
1SAM201902R1004	HK1-20L Auxiliary Contact	HK1-20L	1	piece
1SAM201902R1204	HK1-20LK Auxiliary Contact	HK1-20LK	1	piece
1SAM201903R1002	SK1-20 Signal Contact	SK1-20	1	piece
1SAM201903R1202	SK1-20K Signal Contact	SK1-20K	1	piece
1SAM201903R1001	SK1-11 Signal Contact	SK1-11	1	piece
1SAM201903R1201	SK1-11K Signal Contact	SK1-11K	1	piece
1SAM201903R1003	SK1-02 Signal Contact	SK1-02	1	piece
1SAM201903R1203	SK1-02K Signal Contact	SK1-02K	1	piece
1SAM301901R1002	CK1-20 Short Circuit Signaling Contact	CK1-20	1	piece
1SAM301901R1001	CK1-11 Short Circuit Signaling Contact	CK1-11	1	piece
1SAM301901R1003	CK1-02 Short Circuit Signaling Contact	CK1-02	1	piece
1SAM201910R1001	AA1-24 Shunt Trip	AA1-24	1	piece
1SAM201910R1002	AA1-110 Shunt Trip	AA1-110	1	piece
1SAM201910R1003	AA1-230 Shunt Trip	AA1-230	1	piece
1SAM201910R1004	AA1-400 Shunt Trip	AA1-400	1	piece
1SAM201904R1010	UA1-20 Undervoltage Release	UA1-20	1	piece
1SAM201904R1001	UA1-24 Undervoltage Release	UA1-24	1	piece
1SAM201904R1002	UA1-48 Undervoltage Release	UA1-48	1	piece
1SAM201904R1003	UA1-60 Undervoltage Release	UA1-60	1	piece
1SAM201904R1004	UA1-110 Undervoltage Release	UA1-110	1	piece
1SAM201904R1008	UA1-208 Undervoltage Release	UA1-208	1	piece
1SAM201904R1005	UA1-230 Undervoltage Release	UA1-230	1	piece
1SAM201904R1006	UA1-400 Undervoltage Release	UA1-400	1	piece
1SAM201904R1007	UA1-415 Undervoltage Release	UA1-415	1	piece
1SAM201904R1009	UA1-575 Undervoltage Release	UA1-575	1	piece
1SAM201906R1102	PS1-2-0-65 Busbar	PS1-2-0-65	1	piece
1SAM201906R1112	PS1-2-1-65 Busbar	PS1-2-1-65	1	piece
1SAM201906R1122	PS1-2-2-65 Busbar	PS1-2-2-65	1	piece
1SAM201916R1103	PS1-3-0-100 Busbar	PS1-3-0-100	1	piece
1SAM201906R1103	PS1-3-0-65 Busbar	PS1-3-0-65	1	piece
1SAM201916R1113	PS1-3-1-100 Busbar	PS1-3-1-100	1	piece
1SAM201906R1113	PS1-3-1-65 Busbar	PS1-3-1-65	1	piece
1SAM201916R1123	PS1-3-2-100 Busbar	PS1-3-2-100	1	piece
1SAM201906R1123	PS1-3-2-65 Busbar	PS1-3-2-65	1	piece
1SAM201916R1104	PS1-4-0-100 Busbar	PS1-4-0-100	1	piece
1SAM201906R1104	PS1-4-0-65 Busbar	PS1-4-0-65	1	piece
1SAM201916R1114	PS1-4-1-100 Busbar	PS1-4-1-100	1	piece

1SAM201906R1114	PS1-4-1-65 Busbar	PS1-4-1-65	1	piece
1SAM201906R1124	PS1-4-2-65 Busbar	PS1-4-2-65	1	piece
1SAM201916R1105	PS1-5-0-100 Busbar	PS1-5-0-100	1	piece
1SAM201906R1105	PS1-5-0-65 Busbar	PS1-5-0-65	1	piece
1SAM201916R1115	PS1-5-1-100 Busbar	PS1-5-1-100	1	piece
1SAM201906R1115	PS1-5-1-65 Busbar	PS1-5-1-65	1	piece
1SAM201906R1125	PS1-5-2-65 Busbar	PS1-5-2-65	1	piece
1SAM201907R1101	S1-M1-25 Power Infeed Block	S1-M1-25	1	piece
1SAM201907R1102	S1-M2-25 Power Infeed Block	S1-M2-25	1	piece
1SAM201907R1103	S1-M3-25 Power Infeed Block	S1-M3-25	1	piece
1SAM201913R1103	S1-M3-35 Power Infeed Block	S1-M3-35	1	piece
1SAM201914R1002	S1-PB1-25 Power Infeed Block	S1-PB1-25	1	piece
1SAM301911R1001	TS1-M3-S1 Terminal Spacer	TS1-M3-S1	1	piece
1SAM301912R1001	TS1-M3-S2 Terminal Spacer	S1-M3-S2	1	piece
1SAM201908R1001	BS1-3 Protection Cover	BS1-3	1	piece
1SAM201909R1001	FS116 Screw Fixing Kit	FS116	1	piece
1SAM201914R1001	PB1-1-32 Connecting Link	PB1-1-32	1	piece
GJF1101903R0002	SA2 - Terminals and Installation Material	SA2	1	piece
1SAM201911R1012	IB132-F Enclosure	IB132-F	1	piece
1SAM201911R1010	IB132-G Enclosure	IB132-G	1	piece
1SAM201911R1011	IB132-Y Enclosure	IB132-Y	1	piece
1SAM201912R1010	DMS132-G Door Mounting Kit	DMS132-G	1	piece
1SAM201912R1011	DMS132-Y Door Mounting Kit	DMS132-Y	1	piece
1SAM201909R1021	MSAH1 Shaft Supporter	MSAH1	1	piece
1SAM201920R1011	MSHD-LTB Handles	MSHD-LTB	1	piece
1SAM201920R1012	MSHD-LTY Handles	MSHD-LTY	1	piece
1SAM101923R0002	MSMN Driver	MSMN	1	piece
1SAM101923R0012	MSMNO Driver	MSMNO	1	piece
1SCA101647R1001	OXS6X85 SHAFT	OXS6X85	1	piece
1SCA108043R1001	OXS6X105 SHAFT	OXS6X105	1	piece
1SCA101655R1001	OXS6X130 SHAFT	OXS6X130	1	piece
1SCA101659R1001	OXS6X180 SHAFT	OXS6X180	1	piece

Kategorie

Produkty niskiego napięcia i systemy → Aparatura sterownicza → Wyłączniki silnikowe → Wyłączniki silnikowe

Produkty niskiego napięcia i systemy → Wyłączniki → Wyłączniki silnikowe

