

PRODUCT-DETAILS

OT200E13CLPOT200E13CLP CHANGE-OVER SWITCH



General Information	
Extended Product Type	OT200E13CLP
Product ID	1SCA108548R1001
EAN	6417019399362
Catalog Description	OT200E13CLP CHANGE-OVER SWITCH
Long Description	OT200E13CLP CHANGE-OVER SWITCH, Handle and shaft included, Closed transition

Ordering	
Minimum Order Quantity	1 piece
Customs Tariff Number	85365080
Country of Origin	Finland (FI)

Popular Downloads	
Data Sheet, Technical Information	1SCC303003C0201
Instructions and Manuals	1SCC303008M0203

Dimensions	
Product Net Width	205 mm
Product Net Height	150 mm

Product Net Depth / Length	160 mm
Product Net Weight	205 lb
	4.1 kg

Rated Operational Current AC-21A (1e) (500 V) 200 A (500	Technical	
Current AC-21A (le) (500 y 200 A (600 y 200	Rated Operational	(380 415 V) 200 A
Rated Operational (380 415 V) 200 A Current AC-22A (le) (500 V) 200 A Rated Operational (380 415 V) 200 A Current AC-23A (le) (500 V) 200 A Rated Operational (380 415 V) 200 A Current AC-31B (le) (380 415 V) 200 A Rated Operational (380 415 V) 200 A Current AC-31B (le) (380 415 V) 200 A Rated Operational Power (380 415 V) 110 kW AC-23A (Pe) (500 V) 32 kW Conventional Free-air q = 40 °C 200 A Thermal Current (lip) q = 40 °C 200 A Conventional Thermal Fully Enclosed 200 A Current (liphe) 12 kW Rated Insulation Voltage (Using) 1000 V Rated Insulation Voltage (Using) 1000 V Rated Operational 6 rs 1 s 8 kiloampere rms Withstand Current (lew) 1000 V Voltage 3 Rated Operational 1000 V Voltage 3 Rated Insulation Voltage (Using) 1 Power Los 4 W Pollution Degree	·	(500 V) 200 A
Current AC-22A (Ie) (500 V) 200 A (500 V) 200		(690 V) 200 A
Rated Operational (380 - 415 V) 200 A Current AC-23A (e) (500 V) 200 A Rated Operational (690 V) 200 A Current AC-31B (e) (380 415 V) 200 A Current AC-31B (e) (380 415 V) 200 A Current AC-33B (e) (380 415 V) 200 A Rated Operational Power (380 415 V) 110 kw AC-23A (P_e) (690 V) 200 kw Conventional Free-air $q = 40 ^\circ$ C 200 A Thermal Current (t_{th}) Fully Enclosed 200 A Current (t_{the}) $q = 40 ^\circ$ C 200 A Rated Impulse $q = 40 ^\circ$ C 200 A Rated Impulse $q = 40 ^\circ$ C 200 A Rated Insulation Voltage (U_{tip}) $q = 40 ^\circ$ C 200 A Rated Insulation Voltage (U_{tip}) $q = 40 ^\circ$ C 200 A Rated Operational $q = 40 ^\circ$ C 200 A Rated Operational $q = 40 ^\circ$ C 200 A Rated Operational $q = 40 ^\circ$ C 200 A Rated Operational $q = 40 ^\circ$ C 200 A Rated Operational $q = 40 ^\circ$ C 200 A Rated Operational $q = 40 ^\circ$ C 200 A Rated Operational $q = 40 ^\circ$	· · · · · · · · · · · · · · · · · · ·	
Rated Operational Current AC-23A (le) (380415 V) 200 A (500 V) 200 A (Current AC-22A (I _e)	
Current AC-23A (le) (500 V) 200 A (690 V) 200 A (690 V) 200 A (690 V) 200 A (690 V) 200 A (200 Current AC-31B (le)) Rated Operational Current AC-31B (le) (380 415 V) 200 A (380 415 V) 200 A (200	Dated Onevational	
Rated Operational Current AC-31B (le) (380 415 V) 200 A Rated Operational Current AC-31B (le) (380 415 V) 200 A Rated Operational Current AC-33B (le) (380 415 V) 200 A Rated Operational Power AC-33A (Pe) (380 415 V) 110 kW AC-23A (Pe) (500 V) 132 kW Conventional Free-air Thermal Current (lith) Pully Enclosed 200 A Conventional Thermal Current (lith) Fully Enclosed 200 A Current (lithe) 12 kV Rated Impulse 12 kV Withstand Voltage (Uimp) 1000 V (Vi) 1000 V Rated Operational Voltage 1000 V (Vi) 1000 V Voltage For 1 s 8 kiloampere rms Withstand Current (lcw) 9 Power Loss 4 W Power Loss 4 W Power Loss 4 W Fourth Pole Position Right Side Fourth Pole Position Right Side Fourth Pole Position Right Side Fourth Pole Type Switched - Simultaneous Function Switches Operating Mechanism Between the Poles	· · · · · · · · · · · · · · · · · · ·	
Current AC-31B (le) (380 415 V) 200 A Rated Operational (380 415 V) 200 A Current AC-33B (le) (380 415 V) 110 kW Rated Operational Power (500 V) 132 kW AC-23A (Pe) (500 V) 132 kW Conventional Free-air q = 40 °C 200 A Thermal Current (lth) Fully Enclosed 200 A Conventional Thermal Fully Enclosed 200 A Current (lthe) 12 kW Rated Impulse 12 kW Withstand Voltage (Uimp) 1000 V Rated Insulation Voltage 1000 V (li) 1000 V Rated Operational 1000 V Voltage 1000 V Rated Operational 1000 V Voltage 4 W Power Loss 4 W Pollution Degree 3 Handle Cofor Black Handle Type Handle and shaft included Fourth Pole Type Switched - Simultaneous Function Switches Operating Mechanism Between the Poles Distance Between 13 (Between the Poles Distance Between	Carrone 157 (ve)	
Rated Operational Current AC-33B (le) (380 415 V) 200 A Rated Operational Power AC-23B (le) (380 415 V) 110 kW (500 V) 132 kW (500 V) 200 kW Conventional Free-air Power Ac-23A (le) 9 = 40 °C 200 A Thermal Current (lth) Fully Enclosed 200 A Conventional Thermal Current (lthe) Fully Enclosed 200 A Rated Impulse Without Voltage (Uimp) 12 kW Withstand Voltage (Uimp) Voltage Rated Insulation Voltage (Uimp) 1000 V Voltage 1000 V Voltage For 1 s 8 kiloampere rms Withstand Current (lcw) For 1 s 8 kiloampere rms Power Loss 4 W Entral Loss (Loss and Loss a	Rated Operational	(380 415 V) 200 A
Current AC-33B (le) (380415 V) 110 kW Rated Operational Power AC-23A (Pe) (580 v) 132 kW Conventional Free-air Thermal Current (lth) q = 40 °C 200 A Conventional Thermal Current (lthe) Fully Enclosed 200 A Conventional Thermal Current (lthe) Fully Enclosed 200 A Current (lthe) 12 kW Rated Impulse 12 kW Rated Insulation Voltage (Uimp) 1000 V V(I) 1000 V Voltage 1000 V Rated Short-time for 1 s 8 kiloampere rms Withstand Current (lcw) 6 Power Loss 4 W Power Loss 4 W Pollution Degree 38 ack Handle Color Black Handle Type Handle and shaft included Fourth Pole Position Right Side Fourth Pole Position Skitched - Simultaneous Function Switches Operating Mechanism Between the Poles Mechanism 13 (Between the Poles) Distance Between Standard Phases Top In - Bottom Out, Bottom In - Top Out Porrating M	Current AC-31B (I _e)	
Rated Operational Power AC-23A (Pe) (380 415 V) 110 kW (500 V) 132	Rated Operational	(380 415 V) 200 A
AC-23A (Pe) (500 V) 132 kW Conventional Free-air q = 40 °C 200 A Thermal Current (Ith) Fully Enclosed 200 A Conventional Thermal Fully Enclosed 200 A Current (Ithe) 12 kW Rated Impulse 12 kW Withstand Voltage (Uimp) 1000 V Rated Insulation Voltage (Uimp) 1000 V Rated Operational 1000 V Voltage For 1 s 8 kiloampere rms Withstand Current (Icw) 6 rs 8 kiloampere rms Power Loss 4 W Power Loss 3 Handle Color 8 lack Handle Type Handle and shaft included Fourth Pole Position Right 5tg Fourth Pole Type Switched - Simultaneous Function Switches Operating Mechanism Between the Poles Mechanism Between the Poles 13 (Between the Poles) Distance Between Standard Phases Top In - Bottom Out, Bottom In - Top Out Terminals Top In - Bottom Out, Bottom In - Top Out Terminals Top In - Bottom Out, Bottom In - Top Out	Current AC-33B (I _e)	
Conventional Free-air q = 40 °C 200 A Thermal Current (Ith) Fully Enclosed 200 A Conventional Thermal Fully Enclosed 200 A Current (Ithe) 12 kV Rated Impulse 12 kV Withstand Voltage (Uimp) 1000 V Rated Insulation Voltage 1000 V (Ui) For 1 s 8 kiloampere rms Rated Short-time for 1 s 8 kiloampere rms Withstand Current (Icw) 9 Power Loss 4 W Pollution Degree 3 Handle Color Black Handle Type Handle and shaft included Fourth Pole Position Right Side Fourth Pole Type Switched - Simultaneous Function Switches Operating Mechanism Between the Poles Distance Between Standard Phases Top In - Bottom Out, Bottom In - Top Out Terminals Top In - Bottom Out, Bottom In - Top Out Terminals Top In - Bottom Out, Bottom In - Top Out Terminals Top In - Bottom Out, Bottom In - Top Out Terminals Top In - Bottom Out, Bottom In - Top Out		
Conventional Free-air Thermal Current (Irb) q = 40 °C 200 A Conventional Thermal Current (Irb) Fully Enclosed 200 A Current (Irbe) 12 kV Rated Impulse 12 kV Withstand Voltage (U _{imp}) 1000 V Rated Insulation Voltage (U _{imp}) 1000 V Rated Operational 1000 V Voltage for 1 s 8 kiloampere rms Withstand Current (I _{Cw}) 6 Power Loss 4 W Pollution Degree 3 Handle Color Black Handle Type Handle and shaft included Fourth Pole Position Right Side Fourth Pole Position Switched - Simultaneous Function Switches Operating Mechanism Between the Poles Mechanism 13 (Between the Poles) Distance Between Standard Position of Line Top In - Bottom Out, Bottom In - Top Out Terminals Top In - Bottom Out, Bottom In - Top Out Terminals 4 Operating Mode Front operated Mounting Type Base mounting Number of Poles Front DP20	AC-23A (P _e)	
Thermal Current (Ith) Conventional Thermal Current (Ithe) Rated Impulse Rated Impulse Rated Insulation Voltage (Uimp)) Rated Operational Voltage Rated Operational Voltage Rated Operational Voltage Rated Short-time Rated Short-time Withstand Current (Icw) Power Loss Alandle Color Rated Color Randle Color Randle Color Randle Short-time Sibustion Operational Voltage Randle Short-time Sibustinat Current (Icw) Power Loss Au Pollution Degree Randle Short-time Sibustinated Current (Icw) Randle Color Shack Randle Color Randle Shack Randle Shack Randle Shack Randle Type Randle and shaft included Fourth Pole Position Switched Simultaneous Function Switches Operating Mechanism Between the Poles Mechanism Right Side Fourth Pole Type Switched - Simultaneous Function Switches Operating Mechanism Between the Poles Mechanism Plases Position of Line Treminals Coperating Mode Front operated Mounting Type Base mounting Number of Poles A Degree of Protection Front IP20		
Conventional Thermal Current (Ithe) Rated Impulse Rated Impulse Rated Insulation Voltage (Uimp) Rated Insulation Voltage (Ui) Rated Operational Voltage Rated Short-time Rated Short-time Rows Insulation United Rated Short-time Rated Short-time Rows Insulation United Rated Short-time Rows Insulation Urrent (Icw) Rows Insulation Degree Rated Short-time Rated Short-time Rows Insulation Degree Rated Short-time Rated		q = 40 °C 200 A
Current (Ithe) 2 kV Rated Impulse 12 kV Withstand Voltage (Uimp) 1000 V Rated Insulation Voltage (Uij) 1000 V Rated Operational 1000 V Voltage For 1 s 8 kiloampere rms Withstand Current (Icw) 8 Power Loss 4 W Powler Los 3 Handle Color Black Handle Type Handle and shaft included Fourth Pole Position Right Side Fourth Pole Type Switched - Simultaneous Function Switches Operating Mechanism Between the Poles Mechanism 13 (Between the Poles Mechanism Between the Poles Standard Plasses Top In - Bottom Out, Bottom In - Top Out Terminals Front operated Mounting Type Base mounting Number of Poles Front operated Mounting Type Base mounting Number of Poles Front operated Mean type of Protection Front IP20		Fully Enclosed 200 A
Rated Impulse (Withstand Voltage (Ump)		Tully Efficiosed 200 A
Withstand Voltage (Uimp) Rated Insulation Voltage (Uimp) Rated Operational 1000 V Voltage Rated Short-time for 1 s 8 kiloampere rms withstand Current (Icw) Power Loss 4 W Pollution Degree 3 Handle Color Black Handle Type Handle and shaft included fourth Pole Position Right Side Fourth Pole Position Switched - Simultaneous Function Switches Operating Mechanism Between the Poles Mechanism Standard Phases Position of Line Top In - Bottom Out, Bottom In - Top Out Terminals Operating Mode Front operated Mounting Type Base mounting Number of Poles 4 Degree of Protection Front IP20		12 kV
Rated Insulation Voltage (Ui) Rated Operational Voltage Rated Short-time Rith Short-time Rith Stand Current (Icw) Power Loss Power Loss Handle Color Pollution Degree Handle Type Handle and shaft included Fourth Pole Position Right Side Fourth Pole Type Switched - Simultaneous Function Switches Operating Mechanism Between the Poles Mechanism Phases Position of Line Position of Line Top In - Bottom Out, Bottom In - Top Out Terminals Operating Mode Front operated Mounting Type Base mounting Number of Poles 4 Degree of Protection Front IP20	·	
(Ui) 1000 V Rated Operational Voltage 1000 V Rated Short-time Withstand Current (Icw) for 1 s 8 kiloampere rms Power Loss 4 W Pollution Degree 3 Handle Color Black Handle Type Handle and shaft included Fourth Pole Position Right Side Fourth Pole Type Switched - Simultaneous Function Switches Operating Mechanism Between the Poles Mechanism 13 (Between the Poles) Distance Between Position of Line Top In - Bottom Out, Bottom In - Top Out Terminals Top In - Bottom Out, Bottom In - Top Out Terminals Operating Mode Front operated Mounting Type Base mounting Number of Poles 4 Degree of Protection Front IP20		
Voltage For 1 s 8 kiloampere rms Withstand Current (Icw) For 1 s 8 kiloampere rms Power Loss 4 W Pollution Degree 3 Handle Color Black Handle Type Handle and shaft included Fourth Pole Position Right Side Fourth Pole Type Switched - Simultaneous Function Switches Operating Mechanism Between the Poles Mechanism 13 (Between the Poles) Distance Between Standard Phases Top In - Bottom Out, Bottom In - Top Out Terminals Front operated Mounting Mode Front operated Mounting Type Base mounting Number of Poles 4 Degree of Protection Front IP20		1000 V
Withstand Current (Icw) Power Loss 4 W Pollution Degree 3 Handle Color Black Handle Type Handle and shaft included Fourth Pole Position Right Side Fourth Pole Type Switched - Simultaneous Function Switches Operating Mechanism Between the Poles Mechanism Between the Poles) Distance Between Standard Phases Position of Line Top In - Bottom Out, Bottom In - Top Out Terminals Operating Mode Front operated Mounting Type Base mounting Number of Poles 4 Degree of Protection Front IP20	·	1000 V
Power Loss 4 W Pollution Degree 3 Handle Color Black Handle Type Handle and shaft included Fourth Pole Position Right Side Fourth Pole Type Switched - Simultaneous Function Switches Operating Mechanism Between the Poles Mechanism Standard Phases Distance Between Phases Position of Line Top In - Bottom Out, Bottom In - Top Out Terminals Operating Mode Front operated Mounting Type Base mounting Number of Poles Degree of Protection Front IP20	Rated Short-time	for 1 s 8 kiloampere rms
Pollution Degree 3 Handle Color Black Handle Type Handle and shaft included Fourth Pole Position Right Side Fourth Pole Type Switched - Simultaneous Function Switches Operating Mechanism Between the Poles Mechanism 13 (Between the Poles) Distance Between Phases Position of Line Top In - Bottom Out, Bottom In - Top Out Terminals Operating Mode Front operated Mounting Type Base mounting Number of Poles Degree of Protection Front IP20	Withstand Current (I _{cw})	
Handle Color Handle Type Handle Type Handle and shaft included Fourth Pole Position Right Side Fourth Pole Type Switched - Simultaneous Function Switches Operating Mechanism Between the Poles Mechanism 13 (Between the Poles) Distance Between Phases Position of Line Top In - Bottom Out, Bottom In - Top Out Terminals Operating Mode Front operated Mounting Type Base mounting Number of Poles Degree of Protection Front IP20	Power Loss	4 W
Handle Type Handle and shaft included Fourth Pole Position Right Side Fourth Pole Type Switched - Simultaneous Function Switches Operating Mechanism Between the Poles Mechanism 13 (Between the Poles) Distance Between Position of Line Standard Phases Position of Line Trop In - Bottom Out, Bottom In - Top Out Terminals Pronting Mode Front operated Mounting Type Base mounting Number of Poles Potection Front IP20	Pollution Degree	3
Fourth Pole Position Right Side Fourth Pole Type Switched - Simultaneous Function Switches Operating Mechanism Between the Poles Mechanism 13 (Between the Poles) Distance Between Phases Position of Line Top In - Bottom Out, Bottom In - Top Out Terminals Operating Mode Front operated Mounting Type Base mounting Number of Poles Degree of Protection Front IP20	Handle Color	Black
Fourth Pole Type Switched - Simultaneous Function Switches Operating Mechanism Between the Poles Mechanism 13 (Between the Poles) Distance Between Standard Phases Position of Line Top In - Bottom Out, Bottom In - Top Out Terminals Operating Mode Front operated Mounting Type Base mounting Number of Poles Degree of Protection Front IP20	Handle Type	Handle and shaft included
Switches Operating Mechanism Between the Poles Mechanism 13 (Between the Poles) Distance Between Standard Phases Position of Line Top In - Bottom Out, Bottom In - Top Out Terminals Operating Mode Front operated Mounting Type Base mounting Number of Poles 4 Degree of Protection Front IP20	Fourth Pole Position	Right Side
Mechanism13 (Between the Poles)Distance Between PhasesStandardPosition of Line TerminalsTop In - Bottom Out, Bottom In - Top Out TerminalsOperating ModeFront operatedMounting TypeBase mountingNumber of Poles4Degree of ProtectionFront IP20	Fourth Pole Type	Switched - Simultaneous Function
Distance Between Phases Position of Line Top In - Bottom Out, Bottom In - Top Out Terminals Operating Mode Front operated Mounting Type Base mounting Number of Poles Degree of Protection Front IP20	Switches Operating	Mechanism Between the Poles
Phases Position of Line Top In - Bottom Out, Bottom In - Top Out Terminals Operating Mode Front operated Mounting Type Base mounting Number of Poles 4 Degree of Protection Front IP20	Mechanism	13 (Between the Poles)
Terminals Operating Mode Front operated Mounting Type Base mounting Number of Poles 4 Degree of Protection Front IP20		Standard
Mounting TypeBase mountingNumber of Poles4Degree of ProtectionFront IP20		Top In - Bottom Out, Bottom In - Top Out
Number of Poles 4 Degree of Protection Front IP20	Operating Mode	Front operated
Number of Poles 4 Degree of Protection Front IP20	Mounting Type	Base mounting
		4
	Degree of Protection	Front IP20
	Transition Type	Closed

Environmental

Environmental	1SCC303050D0201
Information	

Certificates and Declarations (Document Number)

Declaration of Conformity - CE	1SCC303045D2702
Environmental Information	1SCC303050D0201
Instructions and Manuals	1SCC303008M0203
RoHS Information	1SCC301149D0202

Container Information	
Package Level 1 Units	1 piece
Package Level 1 Width	170 mm
Package Level 1 Depth / Length	270 mm
Package Level 1 Height	185 mm
Package Level 1 Gross Weight	4.2 kg
Package Level 1 EAN	6417019399362

Classifications	
Object Classification Code	Q
ETIM 5	EC000216 - Switch disconnector
ETIM 6	EC000216 - Switch disconnector
ETIM 7	EC000216 - Switch disconnector
WEEE Category	5. Small Equipment (No External Dimension More Than 50 cm)
E-Number (Finland)	3641610

Categories

 $Low\ Voltage\ Products\ and\ Systems \rightarrow Switches \rightarrow Change-over\ and\ Transfer\ Switches \rightarrow Manual\ Change-over\ Switches$

