

Isolation amplifier - MACX MCR-EX-SL-NAM-NAM - 2866006

Please be informed that the data shown in this PDF Document is generated from our Online Catalog. Please find the complete data in the user's documentation. Our General Terms of Use for Downloads are valid (<http://phoenixcontact.com/download>)



Ex i NAMUR signal conditioner. For operating Ex i proximity sensors and switches in the Ex area. Passive transistor output (resistive according to EN 60947-5-6), line fault transparency, up to SIL 2 according to IEC 61508; screw connection.

Your advantages

- ✓ Signal input: intrinsically safe [Ex ia]; for NAMUR proximity sensors (EN 60947-5-6) or switch contacts
- ✓ Signal output with resistive behavior (transistor), according to EN 60947-5-6
- ✓ Signal output with line fault transparency, line fault indication directly via the signal output to SPS or PLS
- ✓ Up to 5 kHz switching frequency
- ✓ Direction of operation can be selected
- ✓ Line fault detection (LFD) can be enabled and disabled
- ✓ SIL 2 according to IEC 61508/EN 61508
- ✓ 3-way electrical isolation
- ✓ Power supply and error indication possible via DIN rail connector
- ✓ Plug-in connection terminals, screw connection technology
- ✓ Installation in zone 2 permitted
- ✓ Housing width: 12.5 mm



Key Commercial Data

Packing unit	1 pc
GTIN	 4 046356 667876
GTIN	4046356667876
Weight per Piece (excluding packing)	140.000 g
Custom tariff number	85365019
Country of origin	Germany

