



LOAD FEEDER FUSELESS DIRECT STARTING, AC
400V, SIZE S2 22...32 A,
AC 110 V, 50 HZ, SCREW CONNECTION,
ON ADAPTER FOR SCREW AND SNAP-ON MOUNTING
TYPE OF COORDIN. 2,
IQ = 50 KA

General technical data:

product brand name		SIRIUS
Product designation		non-fused load feeder
Design of the product		direct starter
Size of the load feeder		S2
Protection class IP / on the front		IP20
Degree of pollution		3
Insulation voltage / rated value	V	690
Installation altitude / at a height over sea level / maximum	m	2,000
Ambient temperature		
• during storage	°C	-55 ... +80
• during operating	°C	-20 ... +70
Resistance against shock		8g
Impulse voltage resistance / rated value	kV	6
Reference code		
• according to DIN 40719 extended according to IEC 204-2 / according to IEC 750		Q
• according to DIN EN 61346-2		Q
Type of assignment		2
Mechanical operating cycles as operating time / of the contactor / typical		10,000,000

Manufacturer article number		
• of the standard mounting rail adapter included in the scope of supply • of the circuit-breakers included in the scope of supply • of the contactor included in the scope of supply • of the link module included in the scope of supply		3RA1932-1AA00 3RV1031-4EA10 3RT1034-1AF00 3RA1931-1AA00
Design of the switching contact		electromechanical
Type of the motor protection		bimetal
Adjustable response current		
• of the current-dependent overload release	A	22 ... 32

Communication/ Protocol:		
Product function / bus-communication		No
Protocol / is supported		
• AS interface protocol • PROFIBUS DP protocol • PROFINET protocol		No No No

Main circuit:		
Number of poles / for main current circuit		3
Operating voltage / at AC-3 / rated value / maximum	V	400
Operating current / at AC-3 / at 400 V / rated value	A	29
Service power / at AC-3 / at 400 V / rated value	kW	15
Off-load operating frequency	1/s	15

Control circuit/ Control:		
Voltage type / of control feed voltage		AC
Control supply voltage frequency / 1		
• rated value	Hz	50
Control supply voltage / 1		
• at 50 Hz / for AC • rated value	V	110

Auxiliary circuit:		
Product extension / auxiliary switch		Yes
Number of NC contacts / for auxiliary contacts		0
Number of NO contacts / for auxiliary contacts		0
Number of changeover contacts / for auxiliary contacts		0

Inputs/ Outputs:		
Number of digital inputs		0

Short-circuit:		
Product function / short circuit protection		Yes
Design of the short-circuit protection		circuit-breakers
Breaking capacity limit short-circuit current (I _{cu}) / at 400 V / rated value	kA	50

Installation/ mounting/ dimensions:		
mounting position		bei senkrechter Montageebene +/-90° drehbar, bei senkrechter Montageebene +/- 22,5° nach vorne und hinten kippbar
Mounting type		snap-on fastening on 35 mm standard rail
Width	mm	55
Height	mm	295
Depth	mm	173
Distance, to be maintained, to the ranks assembly / sideways	mm	0
Distance, to be maintained, to earthed part		
• forwards	mm	10
• backwards	mm	0
• upwards	mm	50
• sideways	mm	10
Distance, to be maintained, conductive elements		
• forwards	mm	10
• backwards	mm	10
• downwards	mm	0
• sideways	mm	50

Connections/ terminals:		
Design of the electrical connection / for main current circuit		screw-type terminals
Type of the connectable conductor cross-section		
• for main contacts		
• solid		0.7 ... 35 mm ² , 2x (0.75 ... 25 mm ²)
• stranded		0.7 ... 35 mm ² , 2x (0.75 ... 25 mm ²)
• finely stranded / with conductor end processing		0.75 ... 25 mm ² , 2x (0.75 ... 16 mm ²)
• for AWG conductors / for main contacts		2x (30 ... 2)
Verification of suitability		UL / CSA / CCC / GL / LRS / BV / DNV / PRS

Certificates/ approvals:

General Product Approval	For use in hazardous locations	Declaration of Conformity
--------------------------	--------------------------------	---------------------------



Shipping Approval



other

[other](#)

[Environmental Confirmations](#)

Further information:

Information- and Downloadcenter (Catalogs, Brochures,...)

<http://www.siemens.com/industrial-controls/catalogs>

Industry Mall (Online ordering system)

<http://www.siemens.com/industrial-controls/mall>

Cax online generator



<http://www.siemens.com/cax>

Service&Support (Manuals, Certificates, Characteristics, FAQs,...)

<http://support.automation.siemens.com/WW/view/en/3RA1130-4EB34-0AF0/all>

Image database (product images, 2D dimension drawings, 3D models, device circuit diagrams, ...)

http://www.automation.siemens.com/bilddb/cax_en.aspx?mlfb=3RA1130-4EB34-0AF0



last change:

Jul 28, 2014