# **Product data sheet**



CONTACTOR ASSEMBLY,
WYE-DELTA (COMPLETELY MOUNTED) WITH LATERAL
TIMING RELAY,
AC-3, 11KW/400V, 3-POLE,
SIZE S0,S0,S0,EL. LOCKED,
CAGE CLAMP TERMINAL,
24V AC,50/60 HZ RC ELEMENTS MOUNTED

General details:		
product brand name		SIRIUS
Product designation		contactor assembly
Product function		wye-delta-contactor
Size of the contactor		S0, S0, S0
Protection class IP / on the front		IP20
Degree of pollution		3
Insulation voltage / with degree of pollution 3 / rated value	V	690
Installation altitude / at a height over sea level / maximum	m	2,000
Ambient temperature		
during operating	°C	-25 +60
during storage	°C	-55 +80
during transport	°C	-55 +80
Reference code		
<ul> <li>according to DIN 40719 extended according to IEC 204-2 / according to IEC 750</li> </ul>		К
• according to DIN EN 61346-2		Q
Mechanical operating cycles as operating time		
• of the main contacts / typical		10,000,000
of the auxiliary contacts / typical		10,000,000

of the contactor with added auxiliary switch block / typical	10,000,000
--	------------

Main circuit:		
Number of poles / for main current circuit		3
Number of NC contacts / for main contacts		0
Operating voltage / at AC-3 / rated value / maximum	V	690
Operating current / at AC-3 / at 400 V / rated value	A	25
Service power / at AC-3		
• at 400 V / rated value	kW	11
• at 500 V / rated value	kW	15.6
• at 690 V / rated value	kW	19

Control circuit:		
Design of activation		conventional
Design of the surge suppressor		with RC elements
Voltage type / of control feed voltage		AC
Control supply voltage frequency		
• 1 / rated value	Hz	50
• 2 / rated value	Hz	50
Control supply voltage / 1		
• at 50 Hz / for AC / rated value	V	24
• at 60 Hz / for AC / rated value	V	24
operating range factor control supply voltage rated value / of the magnet coil		
• at 50 Hz		
• for AC		0.8 1.1
• at 60 Hz		
• for AC		0.85 1.1
• for DC		0.8 1.1

Auxiliary circuit:		
Product extension / auxiliary switch		Yes
Number of NC contacts / for auxiliary contacts		
• instantaneous switching		4
lagging switching		0
Number of NO contacts / for auxiliary contacts		
• instantaneous switching		4
leading switching		0

Short-circuit:	
Design of the fuse link	
• for short-circuit protection of the auxiliary switch / required	fuse gL/gG: 10 A

• for short-circuit protection of the main circuit

• with type of assignment 1 / required

• at type of coordination 2 / required

fuse gL/gG: 63 A

fuse gL/gG: 25 A

Installation/ mounting/ dimensions:		
mounting position		with vertical mounting surface +/-180° rotatable, with vertical mounting surface +/- 30° tiltable to the front and back
Mounting type		screw and snap-on mounting onto 35 mm standard mounting rail according to DIN EN 50022
Width	mm	158
Height	mm	88
Depth	mm	145
Distance, to be maintained, to the ranks assembly / sidewards	mm	0
Distance, to be maintained, to earthed part / sidewards	mm	0
Distance, to be maintained, conductive elements		
• sidewards	mm	0

### Connection elements and terminals:

Design of the electrical connection / for main current circuit

screw-type terminals

# Certificates/ approvals:

Verification of suitability

CE / UL / CCC / GL / LRS / BV / DNV / RMRS / RINA / PRS / ABS

General Product Approval Declaration of Conformity

**Shipping Approval** 













other

other

Environmental Confirmations

# Sicherheitstechnische Merkmale:

Contact reliability / of the auxiliary contacts

1 faulty switching per 100 million (17 V, 1 mA)

### **Further information:**

Information- and Downloadcenter (Catalogs, Brochures,...)

http://www.siemens.com/industrial-controls/catalogs

Industry Mall (Online ordering system)

http://www.siemens.com/industrial-controls/mall

Cax online generator

http://www.siemens.com/cax

Service&Support (Manuals, Certificates, Characteristics, FAQs,...)

 $\underline{\text{http://support.automation.siemens.com/WW/view/en/3RA1423-8XC22-3EC2/all}}$ 

nttp://www.automation.siemens.com/biiddb/cax_en.aspx?miib=3RA1423-8XC22-3EC2		
last change:	Jul 7, 2014	

Image database (product images, 2D dimension drawings, 3D models, device circuit diagrams, ...)