SIEMENS

Data sheet 3RB3036-1UW1

Overload relay 12.5...50 A Electronic For motor protection Size S2, Class 10E Stand-alone installation Main circuit: Straight-through transformer Auxiliary circuit: Screw Manual-Automatic-Reset



product brand name	SIRIUS
product designation	solid-state overload relay
product type designation	3RB3

size of overload relay	S2
size of contactor can be combined company-specific	S2
power loss [W] for rated value of the current	
 at AC in hot operating state 	0.1 W
• at AC in hot operating state per pole	0.03 W
insulation voltage with degree of pollution 3 at AC rated value	690 V
surge voltage resistance rated value	6 kV
maximum permissible voltage for safe isolation	
 in networks with grounded star point between auxiliary and auxiliary circuit 	300 V
 in networks with grounded star point between auxiliary and auxiliary circuit 	300 V
 in networks with grounded star point between main and auxiliary circuit 	600 V

 in networks with grounded star point between main and auxiliary circuit 	690 V
protection class IP	
• on the front	IP20
of the terminal	IP20
shock resistance	15g / 11 ms
• acc. to IEC 60068-2-27	15g / 11 ms; Signaling contact 97 / 98 in position "Tripped": 8g /
430. to 120 00000 2 2.	11 ms
vibration resistance	1-6 Hz, 15 mm; 6-500 Hz, 20 m/s²; 10 cycles
thermal current	50 A
recovery time	
after overload trip with automatic reset typical	3 min
 after overload trip with remote-reset 	0 min
 after overload trip with manual reset 	0 min
type of protection according to ATEX directive 2014/34/EU	Ex II (2) G [Ex e] [Ex d] [Ex px]; Ex II (2) D [Ex t] [Ex p]
certificate of suitability according to ATEX directive 2014/34/EU	PTB 09 ATEX 3001
reference code acc. to DIN EN 81346-2	F
Ambient conditions	
• installation altitude at height above sea level	2 000 m
maximum	
ambient temperature	
during operation	-25 +60 °C
during storage	-40 +80 °C
during transport	-40 +80 °C
temperature compensation	-25 +60 °C
relative humidity during operation	10 95 %
Main circuit	
number of poles for main current circuit	3
adjustable pick-up value current of the current- dependent overload release	12.5 50 A
operating voltage	
• rated value	690 V
• at AC-3 rated value maximum	690 V
operating frequency rated value	50 60 Hz
operating current rated value	50 A
operating power	
• for three-phase motors at 400 V at 50 Hz	7.5 22 kW
• for AC motors at 500 V at 50 Hz	11 30 kW
• for AC motors at 690 V at 50 Hz	11 45 kW
Auxiliary circuit	

design of the auxiliary switch	integrated
number of NC contacts for auxiliary contacts	1
• note	for contactor disconnection
number of NO contacts for auxiliary contacts	1
• note	for message "tripped"
number of CO contacts	
• for auxiliary contacts	0
operating current of auxiliary contacts at AC-15	
● at 24 V	4 A
● at 110 V	4 A
● at 120 V	4 A
● at 125 V	4 A
● at 230 V	3 A
operating current of auxiliary contacts at DC-13	
● at 24 V	2 A
● at 60 V	0.55 A
● at 110 V	0.3 A
● at 125 V	0.3 A
● at 220 V	0.11 A
Protective and monitoring functions	
trip class	CLASS 10E
design of the overload release	electronic
III /CSA ratings	
UL/CSA ratings	
full-load current (FLA) for three-phase AC motor	
full-load current (FLA) for three-phase AC motor • at 480 V rated value	50 A
full-load current (FLA) for three-phase AC motor	50 A
full-load current (FLA) for three-phase AC motor • at 480 V rated value	
full-load current (FLA) for three-phase AC motor • at 480 V rated value • at 600 V rated value contact rating of auxiliary contacts according to UL Short-circuit protection	50 A
full-load current (FLA) for three-phase AC motor • at 480 V rated value • at 600 V rated value contact rating of auxiliary contacts according to UL Short-circuit protection design of the fuse link	50 A
full-load current (FLA) for three-phase AC motor • at 480 V rated value • at 600 V rated value contact rating of auxiliary contacts according to UL Short-circuit protection design of the fuse link • for short-circuit protection of the main circuit	50 A B600 / R300
full-load current (FLA) for three-phase AC motor • at 480 V rated value • at 600 V rated value contact rating of auxiliary contacts according to UL Short-circuit protection design of the fuse link • for short-circuit protection of the main circuit — with type of coordination 1 required	50 A B600 / R300 gG: 250 A
full-load current (FLA) for three-phase AC motor • at 480 V rated value • at 600 V rated value contact rating of auxiliary contacts according to UL Short-circuit protection design of the fuse link • for short-circuit protection of the main circuit — with type of coordination 1 required — with type of assignment 2 required	50 A B600 / R300 gG: 250 A gG: 200 A
full-load current (FLA) for three-phase AC motor • at 480 V rated value • at 600 V rated value contact rating of auxiliary contacts according to UL Short-circuit protection design of the fuse link • for short-circuit protection of the main circuit — with type of coordination 1 required	50 A B600 / R300 gG: 250 A
full-load current (FLA) for three-phase AC motor • at 480 V rated value • at 600 V rated value contact rating of auxiliary contacts according to UL Short-circuit protection design of the fuse link • for short-circuit protection of the main circuit — with type of coordination 1 required — with type of assignment 2 required • for short-circuit protection of the auxiliary switch	50 A B600 / R300 gG: 250 A gG: 200 A
full-load current (FLA) for three-phase AC motor • at 480 V rated value • at 600 V rated value contact rating of auxiliary contacts according to UL Short-circuit protection design of the fuse link • for short-circuit protection of the main circuit — with type of coordination 1 required — with type of assignment 2 required • for short-circuit protection of the auxiliary switch required	50 A B600 / R300 gG: 250 A gG: 200 A
full-load current (FLA) for three-phase AC motor • at 480 V rated value • at 600 V rated value contact rating of auxiliary contacts according to UL Short-circuit protection design of the fuse link • for short-circuit protection of the main circuit — with type of coordination 1 required — with type of assignment 2 required • for short-circuit protection of the auxiliary switch required	50 A B600 / R300 gG: 250 A gG: 200 A fuse gG: 6 A
full-load current (FLA) for three-phase AC motor • at 480 V rated value • at 600 V rated value contact rating of auxiliary contacts according to UL Short-circuit protection design of the fuse link • for short-circuit protection of the main circuit — with type of coordination 1 required — with type of assignment 2 required • for short-circuit protection of the auxiliary switch required Installation/ mounting/ dimensions mounting position	50 A B600 / R300 gG: 250 A gG: 200 A fuse gG: 6 A
full-load current (FLA) for three-phase AC motor • at 480 V rated value • at 600 V rated value contact rating of auxiliary contacts according to UL Short-circuit protection design of the fuse link • for short-circuit protection of the main circuit — with type of coordination 1 required — with type of assignment 2 required • for short-circuit protection of the auxiliary switch required Installation/ mounting/ dimensions mounting position mounting type	50 A B600 / R300 gG: 250 A gG: 200 A fuse gG: 6 A any stand-alone installation

Connections/ Terminals	
product function	
 removable terminal for auxiliary and control circuit 	Yes
type of electrical connection	
for main current circuit	straight-through transformers
 for auxiliary and control current circuit 	screw-type terminals
arrangement of electrical connectors for main current circuit	Top and bottom
type of connectable conductor cross-sections	
• for main contacts	
— single or multi-stranded	1x (1 50 mm²), 2x (1 35 mm²)
 type of connectable conductor cross-sections for auxiliary contacts 	
— solid	1x (0.5 4 mm²), 2x (0.5 2.5 mm²)
— single or multi-stranded	1x (0,5 4 mm²), 2x (0,5 2,5 mm²)
 finely stranded with core end processing 	1x (0.5 2.5 mm²), 2x (0.5 1.5 mm²)
 type of connectable conductor cross-sections at AWG conductors for auxiliary contacts 	1x (20 14), 2x (20 14)
tightening torque	
 for auxiliary contacts with screw-type terminals 	0.8 1.2 N·m
design of screwdriver shaft	Diameter 5 to 6 mm
size of the screwdriver tip	Pozidriv PZ 2
design of the thread of the connection screw	
 of the auxiliary and control contacts 	M3
Communication/ Protocol	
type of voltage supply via input/output link master	No
Electromagnetic compatibility	
conducted interference	
• due to burst acc. to IEC 61000-4-4	2 kV (power ports), 1 kV (signal ports) corresponds to degree of severity 3
 due to conductor-earth surge acc. to IEC 61000-4-5 	2 kV (line to earth) corresponds to degree of severity 3
 due to conductor-conductor surge acc. to IEC 61000-4-5 	1 kV (line to line) corresponds to degree of severity 3
 due to high-frequency radiation acc. to IEC 61000-4-6 	10 V in frequency range 0.15 to 80 MHz, modulation 80 $\%$ AM with 1 kHz
field-bound parasitic coupling acc. to IEC 61000-4-3	10 V/m
electrostatic discharge acc. to IEC 61000-4-2	6 kV contact discharge / 8 kV air discharge
Display	
display version	
• for switching status	Slide switch

Certificates/ approvals

General Product Approval

EMC

For use in hazardous locations













Declaration of Conformity

Test Certificates

Marine / Shipping



Miscellaneous

Type Test Certificates/Test Report

Special Test Certificate





Marine / Shipping

other









Confirmation

Further information

Information- and Downloadcenter (Catalogs, Brochures,...)

https://www.siemens.com/ic10

Industry Mall (Online ordering system)

https://mall.industry.siemens.com/mall/en/en/Catalog/product?mlfb=3RB3036-1UW1

Cax online generator

http://support.automation.siemens.com/WW/CAXorder/default.aspx?lang=en&mlfb=3RB3036-1UW1

Service&Support (Manuals, Certificates, Characteristics, FAQs,...)

https://support.industry.siemens.com/cs/ww/en/ps/3RB3036-1UW1


Image database (product images, 2D dimension drawings, 3D models, device circuit diagrams, EPLAN macros, ...) http://www.automation.siemens.com/bilddb/cax_de.aspx?mlfb=3RB3036-1UW1&lang=en


Characteristic: Tripping characteristics, I2t, Let-through current


https://support.industry.siemens.com/cs/ww/en/ps/3RB3036-1UW1/char

Further characteristics (e.g. electrical endurance, switching frequency)

http://www.automation.siemens.com/bilddb/index.aspx?view=Search&mlfb=3RB3036-1UW1&objecttype=14&gridview=view1







last modified: 09/23/2020