

withdrawable circuit breaker without guide frame 3-pole, size II, IEC
In=800A to 690V, AC50/60Hz Icu=80kA at 500V rear connection
horizontal Overcurrent release ETU 25 LSI protection adjustable
0.4-1 in Motorized/manual operating mechanism with spring
charging motor AC 50/60 Hz 110-127 V AC or 110-125 V DC
Activation 50/60 Hz 110 V AC, 110 V DC With 1st auxiliary release
Shunt release "F", F1 50/60 Hz 110 V AC/110 V DC, 100% on-load
factor without 2nd auxiliary release 2NO+2NC C01= mechanical
switching cycle counter C22= Ready indicator K07= Tripped
signaling contact, 1 CO not possible with option F02 S01= CES
locking device in OFF position (safe OFF/disconnector functionality)
Disconnector condition in compliance with IEC 60947-2

Further information

Industry Online Support (Manuals, Catalogs, Certificates, FAQ, ...)
<https://support.industry.siemens.com/cs/products?mf=ps&lc=en-WW>
Industry Mall (Online ordering system)
<https://mall.industry.siemens.com>

