

Draw-out circuit breaker Without guide frame 3-pole, Size 2, IEC In=1000 A up to 690 V, 50/60 Hz AC Icu=85 kA at 500 V Rear horizontal connection Overcurrent release ETU45 LSIN protection adjustable 0.4-1 in with display and cubicle bus Opt.: Comm. /measuring func./ground fault/ ZSS Motorized/manual operating mechanism with spring charging motor AC 50/60 Hz 208-240 V or 220-250 V DC Activation AC 50/60 Hz 230 V, 220 V DC without 1st auxiliary release without 2nd auxiliary release 4NO+4NC A41= 3WL1- Replacement breaker with technical data as 2018 for use in combination with existing guide frames C11= electrical On with sealing cap not possible with option F02 C22= Ready indicator K07= Tripped signaling contact, 1 CO not possible with option F02 R30= Locking device against opening of the control cabinet door S07= Castell/Fortress in Off position with 4 padlock (Safe Off/disconnector function) Disconnector condition in compliance with IEC 60947-2

Further information

Industry Online Support (Manuals, Catalogs, Certificates, FAQ, ...)
<https://support.industry.siemens.com/cs/products?mf=ps&lc=en-WW>
Industry Mall (Online ordering system)
<https://mall.industry.siemens.com>

