

withdrawable circuit breaker without guide frame 3-pole, size II, IEC In=2000A to 690V, AC50/60Hz Icu=66kA at 500V rear connection horizontal Overcurrent release ETU 76 LSING protection adjustable 0.4-1 in with graphic display U cubicle bus with ground fault protection Opt.: Comm./measuring func./ZSI Motorized/manual operating mechanism with spring charging motor AC 50/60 Hz 110-127 V AC or 110-125 V DC Activation 50/60 Hz 110 V AC, 110 V DC With 1st auxiliary release Shunt release "F", F1 50/60 Hz 110 V AC/110 V DC, 100% on-load factor With 2nd auxiliary release "F", F2 Shunt release 110 V AC/DC 100% on-load factor 6NO+2NC C11= electrical On with sealing cap not possible with option F02 C20= Spring charge status indicator not possible with option F02 C22= Ready indicator C26= Auxiliary switching function 1 Auxiliary release not possible with option F02 C27= Auxiliary switching function 2 Auxiliary release not possible with option F02 K07= Tripped signaling contact, 1 CO not possible with option F02 K12= Remote reset solenoid 120 V AC/125 V DC

Further information

Information on the packaging

<https://support.industry.siemens.com/cs/ww/en/view/109813875>

Industry Mall (Online ordering system)

<https://mall.industry.siemens.com/mall/en/en/Catalog/product?mlfb=3WL1220-2NG35-5FF7-Z C11+C20+C22+C26+C27+K07+K12>

Service&Support (Manuals, Certificates, Characteristics, FAQs,...)

<https://support.industry.siemens.com/cs/ww/en/ps/3WL1220-2NG35-5FF7-Z C11+C20+C22+C26+C27+K07+K12>

Image database (product images, 2D dimension drawings, 3D models, device circuit diagrams, ...)

http://www.automation.siemens.com/bilddb/cax_en.aspx?mlfb=3WL1220-2NG35-5FF7-Z C11+C20+C22+C26+C27+K07+K12

CAX-Online-Generator

<http://www.siemens.com/cax>

Tender specifications

<http://www.siemens.com/specifications>



last modified:

1/17/2024

