

withdraw. non-aut. circuit-b. with guide frame 4-pole, size iii, IEC In=5000A to 690V, AC50/60Hz Icu=100kA at 500V rear connection horizontal without overcurrent release
Motorized/manual operating mechanism with spring charging motor AC 50/60 Hz 110-127 V AC or 110-125 V DC
Activation 50/60 Hz 110 V AC, 110 V DC With 1st auxiliary release Shunt release "F", F1 50/60 Hz 110 V AC/110 V DC, 100% on-load factor without 2nd auxiliary release 4NO+4NC
C01= Mechanical switching cycle counter C20= Spring charge status indicator not possible with option F02 C22= Ready-to-close signaling R15= Position signaling switch, withdrawable part 3 changeover contacts R21= Shutter 2-part can be locked with bracket lock R86= RONIS locking device against in isolated position

Further information

Industry Online Support (Manuals, Catalogs, Certificates, FAQ, ...)

<https://support.industry.siemens.com/cs/products?mf=ps&lc=en-WW>

Industry Mall (Online ordering system)

<https://mall.industry.siemens.com>

