

SIMATIC ET 200SP, Analog input module, AI Energy Meter 480V AC ST, suitable for BU type D0, channel diagnostics



General information	
Product type designation	AI Energy Meter 480VAC ST
Firmware version	V4.0
usable BaseUnits	BU type D0, BU20-P12+A0+0B
Supported power supply systems	TT, TN
Product function	
• Voltage measurement	Yes
— without voltage transformer	Yes
— with voltage transformer	Yes
• Current measurement	Yes
— without current transformer	No
— with current transformer	Yes
— with Rogowski coil	No
— with current/voltage transformer	No
• Energy measurement	Yes
• Frequency measurement	Yes
• Power measurement	Yes
• Active power measurement	Yes

• Reactive power measurement	Yes
• Power factor measurement	Yes
• Active factor measurement	No
• Reactive power compensation	No
• Line analysis	No
• I&M data	Yes; I&M0 to I&M3
• Isochronous mode	No
Engineering with	
• STEP 7 TIA Portal configurable/integrated as of version	V13 SP1
• STEP 7 configurable/integrated as of version	V5.5 SP4 and higher
• PROFIBUS as of GSD version/GSD revision	GSD Revision 5
• PROFINET as of GSD version/GSD revision	V2.3
Operating mode	
• Cyclic measured value access	Yes
• Acyclic measured value access	Yes
• Fixed measured value sets	Yes
• Freely definable measured value sets	Yes
CiR – Configuration in RUN	
Reparameterization possible in RUN	Yes
Calibration possible in RUN	Yes
Installation type/mounting	
Mounting position	Any
Supply voltage	
Design of the power supply	Supply via voltage measurement channel L1
Type of supply voltage	AC 100 - 277 V
permissible range, lower limit (AC)	90 V
permissible range, upper limit (AC)	293 V
Line frequency	
• permissible range, lower limit	47 Hz
• permissible range, upper limit	63 Hz
Power loss	
Power loss, typ.	0.6 W
Address area	
Address space per module	
• Inputs	256 byte
• Outputs	12 byte
Hardware configuration	
Automatic encoding	Yes
• Mechanical coding element	Yes

Selection of BaseUnit for connection variants	
• 2-wire connection	BU type D0, BU20-P12+A0+0B
Time of day	
Operating hours counter	
• present	Yes
Analog inputs	
Cycle time (all channels), typ.	50 ms; Time for consistent update of all measured and calculated values (cyclic und acyclic data)
Cable length	
• unshielded, max.	200 m
Analog value generation for the inputs	
Measurement principle	Sigma Delta
Sampling frequency, max.	1 024 kHz
Isochronous mode	
Isochronous operation (application synchronized up to terminal)	No
Interrupts/diagnostics/status information	
Alarms	
• Diagnostic alarm	Yes
• Limit value alarm	Yes
• Hardware interrupt	Yes; Monitoring of up to 16 freely selectable process values (exceeding or undershooting of value)
Diagnostics indication LED	
• Monitoring of the supply voltage (PWR-LED)	Yes
• Channel status display	Yes; Green LED
• for channel diagnostics	Yes; red Fn LED
• for module diagnostics	Yes; green/red DIAG LED
Integrated Functions	
Measuring functions	
• Measuring procedure for voltage measurement	TRMS
• Measuring procedure for current measurement	TRMS
• Type of measured value acquisition	seamless
• Curve shape of voltage	Sinusoidal or distorted
• Buffering of measured variables	Yes
• Parameter length	74 byte
• Bandwidth of measured value acquisition	2 kHz; Harmonics: 39 / 50 Hz, 32 / 60 Hz
Measuring range	
— Frequency measurement, min.	45 Hz
— Frequency measurement, max.	65 Hz
Measuring inputs for voltage	

— Measurable line voltage between phase and neutral conductor	277 V
— Measurable line voltage between the line conductors	480 V
— Measurable line voltage between phase and neutral conductor, min.	90 V
— Measurable line voltage between phase and neutral conductor, max.	293 V
— Measurable line voltage between the line conductors, min.	155 V
— Measurable line voltage between the line conductors, max.	508 V
— Measurement category for voltage measurement in accordance with IEC 61010-2-030	CAT II; CAT III in case of guaranteed protection level of 1.5 kV
— Internal resistance line conductor and neutral conductor	3.4 MΩ
— Power consumption per phase	20 mW
— Impulse voltage resistance 1,2/50μs	1 kV

Measuring inputs for current

— measurable relative current (AC), min.	1 %; Relative to the secondary rated current 5 A
— measurable relative current (AC), max.	100 %; Relative to the secondary rated current 5 A
— Continuous current with AC, maximum permissible	5 A
— Apparent power consumption per phase for measuring range 5 A	0.6 V·A
— Rated value short-time withstand current restricted to 1 s	100 A
— Input resistance measuring range 0 to 5 A	25 mΩ; At the terminal
— Zero point suppression	Parameterizable: 2 ... 250 mA, default 50 mA
— Surge strength	10 A; for 1 minute

Accuracy class according to IEC 61557-12

— Measured variable voltage	0,2
— Measured variable current	0,2
— Measured variable apparent power	0.5
— Measured variable active power	0.5
— Measured variable reactive power	1
— Measured variable power factor	0.5
— Measured variable active energy	0.5
— Measured variable reactive energy	1
— Measured variable neutral current	0.5; calculated
— Measured variable phase angle	±1 °; not covered by IEC 61557-12
— Measured variable frequency	0.05

Potential separation	
Potential separation channels	
• between the channels	No
• between the channels and backplane bus	Yes; 3 700V AC (type test) CAT III
Isolation	
Isolation tested with	2 300V AC for 1 min. (type test)
Ambient conditions	
Ambient temperature during operation	
• horizontal installation, min.	0 °C
• horizontal installation, max.	60 °C
• vertical installation, min.	0 °C
• vertical installation, max.	50 °C
Altitude during operation relating to sea level	
• Ambient air temperature-barometric pressure-altitude	On request: Ambient temperatures lower than 0 °C (without condensation) and/or installation altitudes greater than 2 000 m
Dimensions	
Width	20 mm
Height	73 mm
Depth	58 mm
Weights	
Weight (without packaging)	45 g
Other	
Data for selecting a voltage transformer	
• Secondary side, max.	296 V
Data for selecting a current transformer	
• Burden power current transformer x/1A, min.	As a function of cable length and cross section, see device manual
• Burden power current transformer x/5A, min.	As a function of cable length and cross section, see device manual
last modified:	04/13/2018