SIEMENS

Data sheet

6GK5201-3BH00-2BA3

Product type designation



SCALANCE X201-3P IRT

SCALANCE X201-3PIRT MANAGED IE IRT SWITCH, 1 X 10/100MBIT/S RJ45 PORTS, 3 X 100MBIT/S POF SC RJ PORTS, FAULT SIGNAL CONTACT WITH SET BUTTON, REDUNDANT POWER SUPPLY, PROFINET-IO DEVICE, NETWORK MANAGEMENT, RED.- MANAGER INTEGRATED, INCL. ELECTRON. MANUAL ON CD, C-PLUG OPTIONAL

Transmission rate		
Transfer rate	10 Mbit/s, 100 Mbit/s	
Interfaces		
Number of electrical/optical connections		
for network components or terminal equipment / maximum	4	
Design of electrical/optical connections / for network components or terminal equipment	SC RJ	
Type of electrical connection		
• for network components or terminal equipment	RJ45 port	
Number of optical interfaces		
for fiber optic cable / at 100 Mbit/s	3	
Design of the optical interface		
• for fiber optic cable / at 100 Mbit/s	SC-RJ/POF port	
Connectable optical power relative to 1 mW		
• of the transmitter output	-82	
Optical sensitivity relating to 1 mW / of the receiver input / minimum	-25 dB	

Damping ratio / of the FOC transmission link /	0 dB
minimum necessary	
Range / at the optical interface / depending on the	0 0.05 km
optical fiber used	
Interfaces / for communication / integrated	
Number of electrical connections / for network	1
components or terminal equipment	
Number of 100 Mbit/s SC ports	
• for multimode	3
Number of 1000 Mbit/s LC ports	
• for multimode	0
• for single mode (LD)	0
Interfaces / others	
Number of electrical connections	
• for signaling contact	1
• for power supply	1
for redundant voltage supply	1
Type of electrical connection	
for signaling contact	2-pole terminal block
• for power supply	4-pole terminal block
design of the removable storage	
• C-PLUG	Yes
Signal-Inputs/outputs	
Operating voltage / of the signaling contacts	24.1/
Operating voltage / of the signaling contacts • at DC / Rated value	24 V
Operating voltage / of the signaling contacts • at DC / Rated value Operating current / of the signaling contacts	
Operating voltage / of the signaling contacts • at DC / Rated value	24 V 0.1 A
Operating voltage / of the signaling contacts • at DC / Rated value Operating current / of the signaling contacts	
Operating voltage / of the signaling contacts • at DC / Rated value Operating current / of the signaling contacts • at DC / maximum	
Operating voltage / of the signaling contacts • at DC / Rated value Operating current / of the signaling contacts • at DC / maximum Supply voltage, current consumption, power loss	0.1 A
Operating voltage / of the signaling contacts • at DC / Rated value Operating current / of the signaling contacts • at DC / maximum Supply voltage, current consumption, power loss Type of voltage / of the supply voltage	0.1 A
Operating voltage / of the signaling contacts • at DC / Rated value Operating current / of the signaling contacts • at DC / maximum Supply voltage, current consumption, power loss Type of voltage / of the supply voltage Supply voltage	0.1 A DC
Operating voltage / of the signaling contacts • at DC / Rated value Operating current / of the signaling contacts • at DC / maximum Supply voltage, current consumption, power loss Type of voltage / of the supply voltage Supply voltage • external	0.1 A DC 24 V
Operating voltage / of the signaling contacts • at DC / Rated value Operating current / of the signaling contacts • at DC / maximum Supply voltage, current consumption, power loss Type of voltage / of the supply voltage Supply voltage • external • external	0.1 A DC 24 V 18 32 V
Operating voltage / of the signaling contacts • at DC / Rated value Operating current / of the signaling contacts • at DC / maximum Supply voltage, current consumption, power loss Type of voltage / of the supply voltage Supply voltage • external • external Product component / fusing at power supply input	0.1 A DC 24 V 18 32 V Yes
Operating voltage / of the signaling contacts • at DC / Rated value Operating current / of the signaling contacts • at DC / maximum Supply voltage, current consumption, power loss Type of voltage / of the supply voltage Supply voltage • external • external Product component / fusing at power supply input Fuse protection type / at input for supply voltage	0.1 A DC 24 V 18 32 V Yes 1.1 A / 33 V
Operating voltage / of the signaling contacts • at DC / Rated value Operating current / of the signaling contacts • at DC / maximum Supply voltage, current consumption, power loss Type of voltage / of the supply voltage Supply voltage • external • external Product component / fusing at power supply input Fuse protection type / at input for supply voltage Consumed current / maximum	0.1 A DC 24 V 18 32 V Yes 1.1 A / 33 V
Operating voltage / of the signaling contacts • at DC / Rated value Operating current / of the signaling contacts • at DC / maximum Supply voltage, current consumption, power loss Type of voltage / of the supply voltage Supply voltage • external • external Product component / fusing at power supply input Fuse protection type / at input for supply voltage Consumed current / maximum Power loss [W]	0.1 A DC 24 V 18 32 V Yes 1.1 A / 33 V 0.35 A
Operating voltage / of the signaling contacts • at DC / Rated value Operating current / of the signaling contacts • at DC / maximum Supply voltage, current consumption, power loss Type of voltage / of the supply voltage Supply voltage • external • external Product component / fusing at power supply input Fuse protection type / at input for supply voltage Consumed current / maximum Power loss [W] • at DC / at 24 V	0.1 A DC 24 V 18 32 V Yes 1.1 A / 33 V 0.35 A
Operating voltage / of the signaling contacts • at DC / Rated value Operating current / of the signaling contacts • at DC / maximum Supply voltage, current consumption, power loss Type of voltage / of the supply voltage Supply voltage • external • external Product component / fusing at power supply input Fuse protection type / at input for supply voltage Consumed current / maximum Power loss [W] • at DC / at 24 V Permitted ambient conditions	0.1 A DC 24 V 18 32 V Yes 1.1 A / 33 V 0.35 A
Operating voltage / of the signaling contacts • at DC / Rated value Operating current / of the signaling contacts • at DC / maximum Supply voltage, current consumption, power loss Type of voltage / of the supply voltage Supply voltage • external • external Product component / fusing at power supply input Fuse protection type / at input for supply voltage Consumed current / maximum Power loss [W] • at DC / at 24 V Permitted ambient conditions Ambient temperature	0.1 A DC 24 V 18 32 V Yes 1.1 A / 33 V 0.35 A 8.4 W

during transport	-40 +70 °C	
Relative humidity		
 at 25 °C / without condensation / during operation / maximum 	95 %	
Protection class IP	IP30	
Design, dimensions and weight		
Design	compact	
Width	60 mm	
Height	125 mm	
Depth	124 mm	
Net weight	0.78 kg	
Mounting type		
• 35 mm DIN rail mounting	Yes	
wall mounting	Yes	
• S7-300 rail mounting	Yes	
• S7-1500 rail mounting	No	
Product properties, functions, components / genera		
Cascading in the case of a redundant ring / at	50	
reconfiguration time of <\~0.3\~s		
Cascading in cases of star topology	any (depending only on signal propagation time)	
Product functions / management, configuration		
Product function		
Product function • CLI	Yes	
	Yes Yes	
• CLI		
CLIweb-based management	Yes	
CLIweb-based managementMIB support	Yes Yes	
CLIweb-based managementMIB supportTRAPs via email	Yes Yes	
 CLI web-based management MIB support TRAPs via email Configuration with STEP 7 	Yes Yes Yes Yes	
 CLI web-based management MIB support TRAPs via email Configuration with STEP 7 Port mirroring 	Yes Yes Yes Yes No	
 CLI web-based management MIB support TRAPs via email Configuration with STEP 7 Port mirroring multiport mirroring with IRT / PROFINET IO switch 	Yes Yes Yes Yes No No	
 CLI web-based management MIB support TRAPs via email Configuration with STEP 7 Port mirroring multiport mirroring with IRT / PROFINET IO switch PROFINET IO diagnosis 	Yes Yes Yes Yes No No No Yes	
 CLI web-based management MIB support TRAPs via email Configuration with STEP 7 Port mirroring multiport mirroring with IRT / PROFINET IO switch PROFINET IO diagnosis switch-managed 	Yes Yes Yes Yes No No No Yes Yes	
 CLI web-based management MIB support TRAPs via email Configuration with STEP 7 Port mirroring multiport mirroring with IRT / PROFINET IO switch PROFINET IO diagnosis switch-managed Protocol / is supported	Yes Yes Yes Yes No No No Yes Yes	
 CLI web-based management MIB support TRAPs via email Configuration with STEP 7 Port mirroring multiport mirroring with IRT / PROFINET IO switch PROFINET IO diagnosis switch-managed Protocol / is supported Telnet 	Yes Yes Yes Yes No No No Yes Yes Yes	
 CLI web-based management MIB support TRAPs via email Configuration with STEP 7 Port mirroring multiport mirroring with IRT / PROFINET IO switch PROFINET IO diagnosis switch-managed Protocol / is supported Telnet HTTP 	Yes Yes Yes Yes No No No Yes Yes Yes Yes Yes	
 CLI web-based management MIB support TRAPs via email Configuration with STEP 7 Port mirroring multiport mirroring with IRT / PROFINET IO switch PROFINET IO diagnosis switch-managed Protocol / is supported Telnet HTTP HTTPS 	Yes Yes Yes Yes No No No Yes Yes Yes Yes Yes Yes	
 CLI web-based management MIB support TRAPs via email Configuration with STEP 7 Port mirroring multiport mirroring with IRT / PROFINET IO switch PROFINET IO diagnosis switch-managed Protocol / is supported Telnet HTTP HTTPS TFTP 	Yes Yes Yes Yes No No No Yes Yes Yes Yes Yes Yes Yes	
 CLI web-based management MIB support TRAPs via email Configuration with STEP 7 Port mirroring multiport mirroring with IRT / PROFINET IO switch PROFINET IO diagnosis switch-managed Protocol / is supported Telnet HTTP HTTPS TFTP FTP 	Yes Yes Yes Yes No No No Yes	
 CLI web-based management MIB support TRAPs via email Configuration with STEP 7 Port mirroring multiport mirroring with IRT / PROFINET IO switch PROFINET IO diagnosis switch-managed Protocol / is supported Telnet HTTP HTTPS TFTP BOOTP 	Yes Yes Yes Yes No No No Yes	
 CLI web-based management MIB support TRAPs via email Configuration with STEP 7 Port mirroring multiport mirroring with IRT / PROFINET IO switch PROFINET IO diagnosis switch-managed Protocol / is supported Telnet HTTP HTTPS TFTP FTP 	Yes Yes Yes Yes No No No Yes	

Identification & maintenance function	
 I&M0 - device-specific information 	Yes
 I&M1 – higher-level designation/location 	Yes
designation	
Protocol / is supported	
• SNMP v1	Yes
• SNMP v2	Yes
• SNMP v3	Yes
Product functions / Diagnosis	
Product function	
Port diagnostics	Yes
 Statistics Packet Size 	Yes
 Statistics packet type 	Yes
Error statistics	Yes
Product functions / DHCP	
Product function	
DHCP client	Yes
Product functions / Redundancy	
Product function	
Ring redundancy	Yes
 High Speed Redundancy Protocol (HRP) 	Yes
 high speed redundancy protocol (HRP) with redundancy manager 	Yes
 high speed redundancy protocol (HRP) with standby redundancy 	Yes
Protocol / is supported / Media Redundancy Protocol (MRP)	Yes
Product function	
 media redundancy protocol (MRP) with redundancy manager 	Yes
 Media Redundancy Protocol for Planned Duplication (MRPD) 	Yes
Passive listening	Yes
Product functions / Security	
Protocol / is supported	
• SSH	Yes
Product functions / Time	
Product function	
SICLOCK support	Yes
Protocol / is supported • NTP	No
- 1411	110

• SNTP Ye	es
-----------	----

Standards, specifications, approvals			
Standard			
• for FM	FM3611: Class 1, Divison 2, Group A, B, C, D / T4, CL.1, Zone 2, GP. IIC, T4		
• for hazardous zone	EN 60079-0 : 2006, EN 60079-15: 2005, II 3 G Ex nA II T4 KEMA 07 ATEX 0145X		
 for safety / from CSA and UL 	UL 60950-1, CSA C22.2 No. 60950-1		
• for hazardous zone / from CSA and UL	ANSI / ISA 12.12.01, CSA C22.2 No. 213-M1987, CL. 1 / Div. 2 / GP. A, B, C, D T4, CL. 1 / Zone 2 / GP. IIC, T4		
• for emitted interference	EN 61000-6-4 (Class A)		
• for interference immunity	EN 61000-6-2		
Certificate of suitability	EN 61000-6-2, EN 61000-6-4		
• CE marking	Yes		
• C-Tick	Yes		
KC approval	Yes		
 Railway application in accordance with EN 50155 	No		
 Railway application in accordance with EN 50124-1 	No		
MTBF / at 40 °C	78.03 y		

Further Information / Internet Links

Internet-Link	ln'	tern	et-L	ink
---------------	-----	------	------	-----

• to website: Selector SIMATIC NET http://www.siemens.com/snst

SELECTION TOOL

• to website: Industrial communication http://www.siemens.com/simatic-net

• to website: Industry Mall

• to website: Information and Download Center http://www.siemens.com/industry/infocenter

• to website: Image database

• to website: CAx Download Manager http://www.siemens.com/cax

• to website: Industry Online Support

https://support.industry.siemens.com

Security information

https://mall.industry.siemens.com

http://automation.siemens.com/bilddb

Security information

Siemens provides products and solutions with industrial security functions that support the secure operation of plants, solutions, machines, equipment and/or networks. They are important components in a holistic industrial security concept. With this in mind, Siemens' products and solutions undergo continuous development. Siemens recommends strongly that you regularly check for product updates. For the secure operation of Siemens products and solutions, it is necessary to take suitable preventive action(e.g. cell protection concept) and integrate each component into a holistic, state-of-the-art industrial security concept. Thirdparty products that may be in use should also be considered. For more information about industrial security, visit http://www.siemens.com/industrialsecurity. To stay informed about product updates as they occur, sign up for a product-specific newsletter. For more information, visit http://support.automation.siemens.com. (V3.4)

last modified:

11.12.2015