

BSH1404P21A1P

AC servo motor BSH - 32.1 Nm - 4000 rpm -
untapped shaft - without brake - IP65

Main

Product or component type	AC servo motors
Component name	BSH
Continuous stall torque	32.1 N.m for LXM05AD57N4 at 380...480 V 3 phases 32.1 N.m for LXM05BD57N4 at 380...480 V 3 phases 32.1 N.m for LXM05CD57N4 at 380...480 V 3 phases
Peak stall torque	63.09 N.m for LXM05AD57N4 at 380...480 V 3 phases 63.09 N.m for LXM05BD57N4 at 380...480 V 3 phases 63.09 N.m for LXM05CD57N4 at 380...480 V 3 phases
Nominal output power	3400 W for LXM05AD57N4 at 380...480 V 3 phases 3400 W for LXM05BD57N4 at 380...480 V 3 phases 3400 W for LXM05CD57N4 at 380...480 V 3 phases
Nominal speed	3000 rpm for LXM05AD57N4 at 380...480 V 3 phases 3000 rpm for LXM05BD57N4 at 380...480 V 3 phases 3000 rpm for LXM05CD57N4 at 380...480 V 3 phases
Maximum mechanical speed	4000 rpm
Product compatibility	LXM05AD57N4 at 380...480 V 3 phases LXM05BD57N4 at 380...480 V 3 phases LXM05CD57N4 at 380...480 V 3 phases
Shaft end	Untapped
IP degree of protection	IP65
Encoder type	Absolute single turn SinCos Hiperface
Encoder feedback resolution	131072 points/turn
Holding brake	Without
Mounting support	International standard flange
Electrical connection	Straight connectors
Number of poles	10

Complementary

Range compatibility	Lexium 05
Nominal torque	10.8 N.m for LXM05AD57N4 at 380...480 V 3 phases 10.8 N.m for LXM05BD57N4 at 380...480 V 3 phases 10.8 N.m for LXM05CD57N4 at 380...480 V 3 phases
Maximum current Irms	95.6 A for LXM05AD57N4 95.6 A for LXM05BD57N4 95.6 A for LXM05CD57N4
Switching frequency	4 kHz for LEX05
Torque constant	1.57 N.m/A rms at 120 °C
Back electromagnetical force (emf) constant	104 V rms/krpm at 120 °C
Rotor inertia	23.7 kg.cm ² without brake
Stator resistance	0.28 Ohm at 20 °C
Stator inductance	3.9 mH at 20 °C
Stator electrical time constant	13.93 ms at 20 °C

The information provided in this documentation contains general descriptions and/or technical characteristics of the performance of the products contained herein. This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications. It is the duty of any such user or integrator to perform the appropriate and complete risk analysis, evaluation and testing of the products with respect to the relevant specific application or use thereof. Neither Schneider Electric Industries SAS nor any of its affiliates or subsidiaries shall be responsible or liable for misuse of the information contained herein.

Maximum radial force Fr	1840 N at 3000 rpm 2110 N at 2000 rpm 2660 N at 1000 rpm
Maximum axial force Fa	0.2 x Fr
Product weight	26.5 kg