



### Main

Range	TeSys
Device short name	GV3D
Product or component type	Shunt trip
Product compatibility	GV3ME

### Complementary

Control circuit voltage	120 V AC 60 Hz 127 V AC 50 Hz 120 V AC 50 Hz 110 V AC 50 Hz 127 V AC 60 Hz
Control circuit voltage limits	0.8...1.1 Un
[Ui] rated insulation voltage	600 V AC CSA C22.2 No 14 690 V AC IEC 60947-1 600 V AC UL 508
Threshold tripping voltage	0.7...0.35 Un
Inrush power in VA	12 VA AC
Inrush power in W	7 W DC
Hold-in power consumption in VA	7 VA AC
Hold-in power consumption in W	2.5 W DC
Operating time	15 ms IEC 60947-1
On-load factor	100 %
Connections - terminals	Screw clamp terminals 2 0.75...2.5 mm <sup>2</sup> flexible with Screw clamp terminals 1 0.75...2.5 mm <sup>2</sup> flexible with Screw clamp terminals 2 1...2.5 mm <sup>2</sup> solid Screw clamp terminals 2 0.75...2.5 mm <sup>2</sup> flexible without Screw clamp terminals 1 1...2.5 mm <sup>2</sup> solid Screw clamp terminals 1 0.75...2.5 mm <sup>2</sup> flexible without
Tightening torque	1.2 N.m screw clamp terminals
Mechanical durability	15000 cycles
Quantity per set	Set of 10
Product weight	0.07 kg

The information provided in this documentation contains general descriptions and/or technical characteristics of the performance of the products contained herein. This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications. It is the duty of any such user or integrator to perform the appropriate and complete risk analysis, evaluation and testing of the products with respect to the relevant specific application or use thereof. Neither Schneider Electric Industries SAS nor any of its affiliates or subsidiaries shall be responsible or liable for misuse of the information contained herein.