



## Main

|                           |                                  |
|---------------------------|----------------------------------|
| Range                     | TeSys                            |
| Device short name         | LA1LC                            |
| Product or component type | Shunt trip                       |
| Product compatibility     | LD4<br>LD5                       |
| Device application        | Control                          |
| Range compatibility       | TeSys Integral contactor breaker |

## Complementary

|                                 |                             |
|---------------------------------|-----------------------------|
| [Uc] control circuit voltage    | 48 V AC 50/60 Hz            |
| Time delay                      | Without time delay          |
| Voltage release type            | Instantaneous<br>Shunt trip |
| Control circuit voltage limits  | 0.7...1.1 Uc                |
| Threshold tripping voltage      | 0.35...0.7 Uc               |
| Inrush power in VA              | 8 VA AC                     |
| Hold-in power consumption in VA | 4 VA AC                     |
| Operating time                  | $\geq 10$ ms                |
| Connections - terminals         | Screw connection            |
| Quantity per set                | Set of 10                   |
| Product weight                  | 0.15 kg                     |

## Contractual warranty

|          |           |
|----------|-----------|
| Warranty | 18 months |
|----------|-----------|