



Main

Range	TeSys
Product name	TeSys LE
Device short name	LE8K
Product or component type	Enclosed DOL reversing starter
Device application	Standard
Material	Polycarbonate
Utilisation category	AC-3
Device composition	Fuse disconnecter Reversing contactor Thermal overload relay ordered separately
[Ie] rated operational current	6 A AC-3
Motor power kW	2.2 kW at 415 V AC 50/60 Hz 2.2 kW at 380/400 V AC 50/60 Hz 1.5 kW at 220/230 V AC 50/60 Hz 3 kW at 440 V AC 50/60 Hz
[Uc] control circuit voltage	230 V AC 50/60 Hz
[Ithe] conventional enclosed thermal current	6 A
Associated fuse rating	10 A 10 x 38 mm aM
Control type	Push-button start up arrow Push-button start down arrow Push-button stop/reset red O

Complementary

Cable entry number	4 cable entry :ISO20 bottom 4 cable entry :2 Pg 13 + 2 Pg 16 bottom 4 cable entry :ISO20 top 4 cable entry :2 Pg 13 + 2 Pg 16 top
Width	175 mm
Height	165 mm
Depth	146 mm
Product weight	1.6 kg

Environment

IP degree of protection	IP65 conforming to IEC 60529
IK degree of protection	IK09 conforming to IEC 60529
Standards	IEC 60947-4-1
Ambient air temperature for operation	-5...40 °C

Offer Sustainability

Sustainable offer status	Not Green Premium product
RoHS	Compliant - since 0925 - Schneider Electric declaration of conformity
Product end of life instructions	Need no specific recycling operations

The information provided in this documentation contains general descriptions and/or technical characteristics of the performance of the products contained herein. This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications. It is the duty of any such user or integrator to perform the appropriate and complete risk analysis, evaluation and testing of the products with respect to the relevant specific application or use thereof. Neither Schneider Electric Industries SAS nor any of its affiliates or subsidiaries shall be responsible or liable for misuse of the information contained herein.