## Product datasheet Characteristics

### ZB5AK1213

white illuminated selector switch head  $\emptyset$ 22 2-position stay put





#### Main

Mani		
Range of product	Harmony XB5	
Product or component type	Head for illuminated selector switch	
Product compatibility	Integral LED	
Device short name	ZB5	
Bezel material	Dark grey plastic	
Mounting diameter	22 mm	
Head type	Standard	
Sale per indivisible quantity	1	
Shape of signaling unit head	Round	
Type of operator	stay put	
Operator profile	White standard handle	-
Operator position information	2 positions 90°	

#### Complementary

Device presentation	Basic element	Ę
	M4 for <2 contacts using single and double blocks in front mounting with integral LED	( ( ( (
	MF1 for <2 contacts using single blocks in front mounting with integral LED MR1 for <2 contacts using single blocks in rear mounting with integral LED	8
	M10 for <2 contacts using single blocks in front mounting with integral LED	tati
	M6 for <2 contacts using single blocks in front mounting with integral LED and transformer	. <u>u</u> C
Electrical composition code	M3 for <4 contacts using single blocks in front mounting with integral LED	
	XALK 25 cut-outs	i at
Station name	XALD 15 cut-outs	2
Mechanical durability	1000000 cycles	,, ,, ,,
Net weight	0.016 kg	
CAD overall depth	43 mm	
CAD overall height	29 mm	<u>ئ</u> ئ
CAD overall width	29 mm	
OAD II - 1-III-	00	<u>u</u>

#### Environment

Protective treatment	TH
Ambient air temperature for storage	-4070 °C
Ambient air temperature for operation	-4070 °C
Overvoltage category	Class II conforming to IEC 60536
IP degree of protection	IP66 conforming to IEC 60529 IP67 IP69 IP69K
NEMA degree of protection	NEMA 13 NEMA 4X
Resistance to high pressure washer	7000000 Pa at 55 °C, distance : 0.1 m
IK degree of protection	IK06 conforming to IEC 50102
Standards	EN/IEC 60947-5-4 JIS C8201-5-1 CSA C22.2 No 14 EN/IEC 60947-5-1 EN/IEC 60947-5-5 UL 508 EN/IEC 60947-1 JIS C8201-1
Product certifications	DNV BV RINA CSA GL LROS (Lloyds register of shipping) UL listed
Vibration resistance	5 gn (f= 2500 Hz) conforming to IEC 60068-2-6
Shock resistance	30 gn (duration = 18 ms) for half sine wave acceleration conforming to IEC 60068-2-27 50 gn (duration = 11 ms) for half sine wave acceleration conforming to IEC 60068-2-27

#### Packing Units

r acking critis		
Package 1 Weight	0.019 kg	
Package 1 Height	0.450 dm	
Package 1 width	0.340 dm	
Package 1 Length	0.540 dm	

### Offer Sustainability

Sustainable offer status	Green Premium product			
REACh Regulation	REACh Declaration			
REACh free of SVHC	Yes			
EU RoHS Directive	Pro-active compliance (Product out of EU RoHS legal scope) EU RoHS Declaration			
Toxic heavy metal free	Yes			
Mercury free	Yes			
RoHS exemption information	Yes			
China RoHS Regulation	China RoHS declaration			
Environmental Disclosure	Product Environmental Profile			
Circularity Profile	End of Life Information			

#### Contractual warranty

Warranty	18 months	

# Product datasheet Dimensions Drawings

## ZB5AK1213

#### **Dimensions**






### ZB5AK1213

Panel Cut-out for Pushbuttons, Switches and Pilot Lights (Finished Holes, Ready for Installation)


Connection by Screw Clamp Terminals or Plug-in Connectors or on Printed Circuit Board



- (1) Diameter on finished panel or support
- For selector switches and Emergency stop buttons, use of an anti-rotation plate type ZB5AZ902 is recommended.  $\varnothing$ 22.5 mm recommended ( $\varnothing$ 22.3  $_0^{+0.4}$ ) /  $\varnothing$ 0.89 in. recommended ( $\varnothing$ 0.88 in.  $_0^{+0.016}$ )
- (2) (3)

Connections	a in mm	a in in.	b in mm	b in in.
By screw clamp terminals or plug-in connector	40	1.57	30	1.18
By Faston connectors	45	1.77	32	1.26
On printed circuit board	30	1.18	30	1.18


### **Detail of Lug Recess**



- Diameter on finished panel or support
- For selector switches and Emergency stop buttons, use of an anti-rotation plate type ZB5AZ902 is recommended.  $\emptyset$ 22.5 mm recommended ( $\emptyset$ 22.3  $_0$   $^{+0.4}$ ) /  $\emptyset$ 0.89 in. recommended ( $\emptyset$ 0.88 in.  $_0$   $^{+0.016}$ )
- (1) (2) (3)

### Pushbuttons, Switches and Pilot Lights for Printed Circuit Board Connection


#### Panel Cut-outs (Viewed from Installer's Side)



- A: 30 mm min. / 1.18 in. min.
- B: 40 mm min. / 1.57 in. min.

#### Printed Circuit Board Cut-outs (Viewed from Electrical Block Side)

#### Dimensions in mm



- A: 30 mm min.
- B: 40 mm min.

#### Dimensions in in.



A: 1.18 in. min. B: 1.57 in. min.

#### General Tolerances of the Panel and Printed Circuit Board

The cumulative tolerance must not exceed 0.3 mm / 0.012 in.: T1 + T2 = 0.3 mm max.

#### Installation Precautions

- Minimum thickness of circuit board: 1.6 mm / 0.06 in.
- Cut-out diameter: 22.4 mm ± 0.1 / 0.88 in. ± 0.004
- Orientation of body/fixing collar ZB5AZ009: ± 2°30' (excluding cut-outs marked a and b).
- Tightening torque of screws ZBZ006: 0.6 N.m (5.3 lbf.in) max.
- Allow for one ZB5AZ079 fixing collar/pillar and its fixing screws:
  - o every 90 mm / 3.54 in. horizontally (X), and 120 mm / 4.72 in. vertically (Y).
  - o with each selector switch head (ZB5AD•, ZB5AJ•, ZB5AG•).

The fixing centers marked a and b are diagonally opposed and must align with those marked 4 and 5.



- (1) (2) (2) Head ZB5AD•
- Panel
- Nut
- Printed circuit board


#### Mounting of Adapter (Socket) ZBZ01•

- 1 2 elongated holes for ZBZ006 screw access
- 2 1 hole Ø 2.4 mm ± 0.05 / 0.09 in. ± 0.002 for centring adapter ZBZ01•
- 3 8 × Ø 1.2 mm / 0.05 in. holes
- 4 1 hole Ø 2.9 mm  $\pm$  0.05 / 0.11 in.  $\pm$  0.002, for aligning the printed circuit board (with cut-out marked a)
- 5 1 elongated hole for aligning the printed circuit board (with cut-out marked b)
- 6 4 holes Ø 2.4 mm / 0.09 in. for clipping in adapter ZBZ01•

Dimensions An + 18.1 relate to the Ø 2.4 mm  $\pm$  0.05 / 0.09 in.  $\pm$  0.002 holes for centring adapter ZBZ01•.

## ZB5AK1213

Electrical Composition Corresponding to Code M3



## ZB5AK1213

Electrical Composition Corresponding to Code M4



## ZB5AK1213

Electrical Composition Corresponding to Codes M6 and P2



## ZB5AK1213

Electrical Composition Corresponding to Codes M5, M10, MF1, MR1 and MF2



## ZB5AK1213

### Legend

Single contact



Double contact



Light block



Possible location



### ZB5AK1213

### Sequence of Contacts Fitted to 2-position Selector Switch Body

#### Position 315°



Push	Position	Тор		1	
		Bottom	Δ		$\triangle$
	Location		Left	$\otimes$	Right
	State		0		0
Contacts	N/O		open		open
	N/C		closed		closed

#### Position 45°



Push	Position	Тор		П	
		Bottom			
	Location		Left	$\otimes$	Right
	State		1		1
Contacts	N/O		closed		closed
	N/C		open		open