

SIMOTICS SD - 250 M - IM B5 - 4p

Client order no.	Item-No.	Offer no.
Order no.	Consignment no.	Project

Remarks

Safe Area

-/-

U	Δ / Y	f	P	P	I	n	M	η ³⁾			cosφ ³⁾			I _A /I _N	M _A /M _N	M _K /M _N	IE-CL
[V]		[Hz]	[kW]	[hp]	[A]	[1/min]	[Nm]	4/4	3/4	2/4	4/4	3/4	2/4	I _I /I _N	T _I /T _N	T _B /T _N	
DOL duty (S1) - 155(F) to 130(B)																	
380	Δ	50	55.00	-/-	102.00	1482	355.0	94.6	95.1	95.0	0.87	0.84	0.76	6.8	2.5	2.9	IE3
660	Y	50	55.00	-/-	58.00	1482	355.0	94.6	95.1	95.0	0.87	0.84	0.76	6.8	2.5	2.9	IE3
440	Δ	60	63.00	-/-	101.00	1782	340.0	94.1	94.5	94.4	0.87	0.84	0.77	6.7	2.4	2.8	IE2
440	Δ	60	55.00	-/-	88.00	1786	295.0	95.4	95.6	95.1	0.86	0.83	0.74	7.6	2.8	3.2	IE3
IM B5 / IM 3001			FS 250 M			IP55	UKCA	IEC/EN 60034		IEC, DIN, ISO, VDE, EN							
Environmental conditions : -20 °C - +40 °C / 1,000 m									Locked rotor time (hot / cold) : 34.9 s 55 s								

Sound level (SPL / SWL) at 50Hz 60Hz	66 / 79 dB(A) ^{2) 3)}	68 / 82 dB(A) ^{2) 3)}	Vibration severity grade	A
Moment of inertia	0.8500 kg m²		Thermal class	F
Bearing DE NDE	6215 Z C3	6215 Z C3	Duty type	S1
bearing lifetime			Direction of rotation	bidirectional
L _{10mh} F _{Rad min} for coupling operation 50 60Hz ¹⁾	40000 h	32000 h	Frame material	cast iron
Regreasing device	Without		Net weight of the motor (IM B3)	420 kg
Grease nipple	-/-		Coating (paint finish)	Standard paint finish C2
Type of bearing	Locating bearing NDE		Color, paint shade	RAL7030
Condensate drainage holes	With (standard)		Motor protection	(A) without (Standard)
External earthing terminal	With (standard)		Method of cooling	IC411 - self ventilated, surface cooled

Terminal box position	top	Max. cross-sectional area	120 mm²
Material of terminal box	cast iron	Cable diameter from ... to ...	34 mm - 42 mm
Type of terminal box	TB1 N01	Cable entry	2xM63x1,5
Contact screw thread	M10	Cable gland	2 plugs

Notes:

I_r/I_n = locked rotor current / current nominal	1) L10mh according to DIN ISO 281 10/2010	3) Value is valid only for DOL operation with motor design IC411
M_r/M_n = locked rotor torque / torque nominal	2) at rated power / at full load	
M_b/M_n = break down torque / nominal torque		

responsible dep.	technical reference	created by	approved by	Technical data are subject to change! There may be discrepancies between calculated and rating plate values.		Link documents	
IN LVM		SPC					
	document type			document status			
	datasheet			released			
	title			document number			
© INNOMOTICS 2023	1LE1503-2CB23-3FA4			rev.	creation date	language	Page
				951	2023-11-08	en	1/1