

PRODUCT-DETAILS

E2.2H/E9 1250 Ekip Hi-Touch LSIG 3p FHR

E2.2H/E9 1250 Ekip Hi-Touch LSIG 3p FHR



General Information

Extended Product Type	E2.2H/E9 1250 Ekip Hi-Touch LSIG 3p FHR
Product ID	1SDA104350R1
EAN	8015644064303
Catalog Description	E2.2H/E9 1250 Ekip Hi-Touch LSIG 3p FHR
Long Description	C.BREAKER SACE EMAX2 E2.2H 1250 FIXED THREE-POLE WITH TERMINALS REAR HORIZONTAL AND SOLID-STATE RELEASE IN AC Ekip/HI-TOUCH-LSIG R 1250 FITTED WITH: 4 AUXILIARY CONTACT AND C.BREAKER IN POSITION OPEN-CLOSED 900V

Ordering

Minimum Order Quantity	1 piece
Customs Tariff Number	85362090
Country of Origin	Italy (IT)

Popular Downloads

Data Sheet, Technical Information	1SDC200023D0209
Instructions and Manuals	1SDH001000R0002

Dimensions

Product Net Width	276 mm
-------------------	--------

Product Net Height	371 mm
Product Net Depth / Length	270 mm
Product Net Weight	41 kg

Technical

Rated Impulse Withstand Voltage (U_{imp})	acc. to IEC 60947-2 12 kV
Rated Insulation Voltage (U_i)	AC 1000 V
Rated Operational Voltage	900 V AC
Rated Short-Circuit Making Capacity (I_{cm})	(800 V AC) 143 kA (900 V AC) 143 kA
Rated Short-time Withstand Current (I_{cw})	for 1 s 65 kA for 3 s 65 kA
Power Loss	176 W
Standards	IEC
Number of Poles	3
Mechanical Durability	25000 cycle 60 cycles per hour

Environmental

RoHS Status	Following EU Directive 2011/65/EU and Amendment 2015/863 July 22, 2019
Environmental Information	ROHS, REACH

Certificates and Declarations (Document Number)

Declaration of Conformity - CE	9AKK107680A4888
Environmental Information	ROHS, REACH
Instructions and Manuals	1SDH001000R0002
Instructions and Manuals (Part 2)	1SDH001316R1002

Container Information

Package Level 1 Units	1 piece
Package Level 1 Width	515 mm
Package Level 1 Depth / Length	515 mm
Package Level 1 Height	610 mm
Package Level 1 Gross Weight	53 kg
Package Level 1 EAN	8015644064303

Classifications

Object Classification Code	Q
ETIM 6	EC000228 - Power circuit-breaker for trafo/generator/installation prot.
ETIM 7	EC000228 - Power circuit-breaker for trafo/generator/installation protection

Categories

Low Voltage Products and Systems → Circuit Breakers → Air Circuit Breakers → Emax 2

Low Voltage Products and Systems → Industries → Solar power → 800V AC

