

PRODUCT-DETAILS

XLP3

XLP3 Fuse Switch Disconnecter



General Information

Extended Product Type	XLP3
Product ID	1SEP101975R0001
EAN	7025840016977
Catalog Description	XLP3 Fuse Switch Disconnecter
Long Description	XLP3,3-pole,630A, without clamps or bolts

Ordering

Minimum Order Quantity	1 piece
Customs Tariff Number	85389099
Country of Origin	China (CN)

Popular Downloads

Data Sheet, Technical Information	1SEC312012D0201
-----------------------------------	-----------------

Dimensions

Product Net Width	250 mm
Product Net Height	330 mm
Product Net Depth / Length	142 mm

Product Net Weight	4.5 kg
--------------------	--------

Technical

Rated Operational Current AC-21B (I _e)	(690 V) 500 A
Rated Operational Current AC-22B (I _e)	(500 V) 630 A
Rated Impulse Withstand Voltage (U _{imp})	Main Circuit 8 kV
Rated Operational Voltage	500 V AC 690 V AC
Rated Frequency (f)	Main Circuit 50/60 Hz
Rated Conditional Short-Circuit Current (I _{nc})	(690 V) 50 kiloampere rms
Handle Type	Front cover 3P
Fuse Size	NH3
Fuse System	DIN
Standards	IEC60947-3
Special Functions	Not Included
Mounting Type	Baseplate
Number of Poles	3
Degree of Protection	IP30
Terminal Type	Lug terminals
Device Type Manager (DTM)	Fuseswitchdisconnector
Fuse Type	NH
Electronic Fuse Monitoring	No

Certificates and Declarations (Document Number)

Declaration of Conformity - CE	1SEP500050P0001
--------------------------------	-----------------

Container Information

Package Level 1 Units	shrink-wrap 1 piece
Package Level 1 Width	250 mm
Package Level 1 Depth / Length	142 mm
Package Level 1 Height	330 mm
Package Level 1 Gross Weight	4.5 kg
Package Level 1 EAN	7025840016977
Package Level 2 EAN	7025840016977

Classifications

Object Classification Code	S
ETIM 4	EC001040 - Fuse switch disconnector
ETIM 5	EC001040 - Fuse switch disconnector
ETIM 6	EC001040 - Fuse switch disconnector
ETIM 7	EC001040 - Fuse switch disconnector
WEEE Category	5. Small Equipment (No External Dimension More Than 50 cm)

Categories

Low Voltage Products and Systems → Fusegear → Fuse Switch Disconnectors → EasyLine

