

PRODUCT-DETAILS

N2301 AN

N2301 AN - Switch 1-gang, 1-way, SP - 3 M - Anthracite



General Information

Extended Product Type	N2301 AN
Product ID	2CLA230100N1801
EAN	8427238085524
Catalog Description	N2301 AN - Switch 1-gang, 1-way, SP - 3 M - Anthracite
Long Description	Color: Anthracite. Rated voltage: 110 - 250 Vac Rated current: 16 AX. Rated power iLED (230/127 Vac): 200/100 W. Screwless terminals Optional: locator LED lamp N2191. Size: 3 modules.

Ordering

EAN	8427238085524
Minimum Order Quantity	10 piece
Customs Tariff Number	85365080

Dimensions

Product Net Width	66 mm
Product Net Height	44 mm
Product Net Weight	0.032 kg

Container Information

Package Level 1 Units	box 10 piece
Package Level 1 Width	0.097 m
Package Level 1 Height	0.06 m
Package Level 1 Depth / Length	0.233 m
Package Level 1 Gross Weight	0.32 kg
Package Level 1 EAN	8427238085524

Environmental

Ambient Air Temperature	Operation -5 ... +35 °C Storage -5 ... +50 °C
-------------------------	--

Additional Information

Actuator Type	Rocker/button
Color	Anthracite
Degree of Protection	IP20
Function	Function lighting: Orientation
Lamp Type	LED exchangeable
Material	Plastic
Mounting Type	Flush mounted (plaster)
Product Main Type	Zenit
Product Name	Switch 1-gang, 1-way, SP - 3 M - Anthracite
Rated Current (I _n)	16 A
Rated Voltage (U _r)	250 V
Replaced Product ID (OLD)	2CL0N230108
Surface Finishing	Surface protection: Decor Surface finishing: Matt

Certificates and Declarations (Document Number)

Data Sheet, Technical Information	9AKK10103A5108
Instructions and Manuals	2CLX210109N1001

Classifications

ETIM 5	EC001590 - Switch
ETIM 6	EC001590 - Switch
ETIM 7	EC001590 - Switch
WEEE Category	5. Small Equipment (No External Dimension More Than 50 cm)

Categories

Low Voltage Products and Systems → Switch Assortments → Flush Mounted Modular Range - Niessen → Design Zenit → Flush Mounted Inserts with Cover Plate → Mechanical Switch / Push Button

Low Voltage Products and Systems → Switch Assortments → Light / LoadControl → Mechanical Switch / Push Button → Mechanical Switch / Push Button - Flush Mounted → Mechanical Switch / Push Button

