

---

PRODUCT-DETAILS

# VLM-1-250/96

## VLM-1-250/96 Analogue voltmeter




---

### General Information

Extended Product Type	VLM-1-250/96
Product ID	2CSG113180R4001
EAN	8012542547303
Catalog Description	VLM-1-250/96 Analogue voltmeter
Long Description	VLM-1-250/96 is an 96x96mm front-panel analogue voltmeter for ac networks. Direct insertion.

---

### Ordering

EAN	8012542547303
Minimum Order Quantity	1 piece
Customs Tariff Number	90303100

---

### Dimensions

Product Net Width	96 mm
Product Net Height	0.096 m
Product Net Depth / Length	53 mm
Product Net Weight	0.400 kg

---

## Container Information

---

Package Level 1 Units	box 1 piece
Package Level 1 Width	0.12 m
Package Level 1 Height	0.1 m
Package Level 1 Depth / Length	0.1 m
Package Level 1 Gross Weight	0.4 kg
Package Level 1 EAN	8012542547303

---

## Environmental

---

Ambient Air Temperature	Operation -40 ... +55 °C
RoHS Status	Following EU Directive 2002/95/EC August 18, 2005 and amendment

---

## Additional Information

---

Accuracy	±1,5%
Current Type	AC
Degree of Protection	IP52
Dimensions	96 mm x 96 mm
Measuring Range	0...250 V
Meter Type	Analogue
Mounting Type	Front-panel
Power Loss	2.4 W
Product Main Type	VLM-1/96
Product Name	Analogue Voltmeter
RoHS Date	31/03/2006 0.00.00
Voltage Range	250 V AC

---

## Certificates and Declarations (Document Number)

---

Data Sheet, Technical Information	9AKK107046A0430
Declaration of Conformity - CE	9AKK106713A5718
Environmental Information	See RoHS Information
Instructions and Manuals	on the product body
RoHS Information	2CSC445003K0201

---

## Classifications

---

ETIM 4	EC002306 - Voltmeter for installation
ETIM 5	EC002306 - Voltmeter for installation
ETIM 6	EC002306 - Voltmeter for installation
ETIM 7	EC002306 - Voltmeter for installation
Object Classification Code	P

WEEE Category

5. Small Equipment (No External Dimension More Than 50 cm)

---

---

## Categories

---

Low Voltage Products and Systems → Modular DIN Rail Products → Energy Efficiency Devices → Front Panel single function instruments

