

PRODUCT-DETAILS

CT4/150

CT4/150 Current transformer



General Information

Extended Product Type	CT4/150
Product ID	2CSG221110R1101
EAN	8012542603702
Catalog Description	CT4/150 Current transformer
Long Description	CT4/150 is used to transform primary currents to..5A secondary currents for c.a. measurement instruments

Ordering

EAN	8012542603702
Minimum Order Quantity	1 piece
Customs Tariff Number	85043121

Dimensions

Product Net Width	0.070 m
Product Net Height	0.080 m
Product Net Depth / Length	0.105 m
Product Net Weight	0.416 kg

Container Information

Package Level 1 Units	1 piece
Package Level 1 Width	0.109 m
Package Level 1 Height	0.044 m
Package Level 1 Depth / Length	0.075 m
Package Level 1 Gross Weight	0.5 kg
Package Level 1 EAN	8012542603702
Package Level 2 Units	1 piece
Package Level 2 Gross Weight	0.390 kg

Environmental

Ambient Air Temperature	Operation -5 ... +50 °C
RoHS Status	Following EU Directive 2002/95/EC August 18, 2005 and amendment

Additional Information

Cable Cross-Section	32 mm
Cable Use	Cable, Horizontal and Vertical bars
Current Limit Function	FS 5
Degree of Protection	IP30
Frequency (f)	50 ... 60 Hz
Mounting Type	Through primary
Power Loss	7 W
Product Main Type	CT
Product Name	Current transformer
Rated Cross-Section	40 x 10 mm
RoHS Date	31/03/2006 0.00.00
Secondary Output Connection	Screw connection

Certificates and Declarations (Document Number)

Data Sheet, Technical Information	9AKK107046A0430
Declaration of Conformity - CE	9AKK106713A5700
Environmental Information	See RoHS Information
Instructions and Manuals	on the product body
RoHS Information	2CSC445004K0201

Classifications

ETIM 4	EC002048 - Current transformer
--------	--------------------------------

ETIM 5	EC002048 - Current transformer
ETIM 6	EC002048 - Current transformer
ETIM 7	EC002048 - Current transformer
Object Classification Code	T
WEEE Category	5. Small Equipment (No External Dimension More Than 50 cm)

Categories

Low Voltage Products and Systems → Modular DIN Rail Products → Energy Efficiency Devices → Current Transformers

