SIEMENS

Data sheet 3KA7154-3AA00

~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~	ECTOR 3	H DISCONNECTOR 3X ⁻	1600A
----------------------------------------	---------	--------------------------------	-------

Model			
Product brand name	SENTRON		
Product designation	Switch disconnector		
Design of the product	Basic versions without handle		
Design of the load switch / Strip form	No		
Type of the driving mechanism / motor drive	No		
General technical data			
Number of poles	3		
Type of device	fixed mounting		
Electrical endurance (switching cycles) / typical	500		
circuit-breaker / Design	3KA715		
Mechanical service life (switching cycles) / typical	4 000		
Type of voltage	AC/DC		
Protection class IP	IP00		
1 Totodott oldss II	11 00		
Electricity			
Operating current / at AC-21 / rated value	1 600 A		
Current / rated value	1 600 A		
Continuous current / rated value	1 600 A		
Main circuit			
Operating voltage			
• rated value	690 V		
• at AC / at 50/60 Hz / rated value	690 V		
• at DC / rated value	440 V		
Suitability			
Suitability for use			
EMERGENCY OFF switch	Yes		
• safety switch	Yes		
•			
Short circuit			
Maximum short-circuit current breaking capacity (Icu) / at 400 V / rated value	100 kA		
Connections			
Type of electrical connection	Busbar connection		
• for main current circuit	flat connector		

Mechanical Design	
Height	306 mm
Width	356 mm
Depth	186 mm
Mounting type	floor mounting
Net weight	18 kg

#### Ambient temperature

-20 °C • during operation / minimum 45 °C • during operation / maximum

#### Certificates

Equipment marking / acc. to DIN EN 61346-2

Q

## **Declaration of Conformity**



### Further information

Information- and Downloadcenter (Catalogs, Brochures,...)

http://www.siemens.com/lowvoltage/catalogs

Industry Mall (Online ordering system)

https://mall.industry.siemens.com/mall/en/en/Catalog/product?mlfb=3KA7154-3AA00

Service&Support (Manuals, Certificates, Characteristics, FAQs,...)

https://support.industry.siemens.com/cs/ww/en/ps/3KA7154-3AA00

Image database (product images, 2D dimension drawings, 3D models, device circuit diagrams, ...) <a href="http://www.automation.siemens.com/bilddb/cax_en.aspx?mlfb=3KA7154-3AA00">http://www.automation.siemens.com/bilddb/cax_en.aspx?mlfb=3KA7154-3AA00</a>

**CAx-Online-Generator** 

http://www.siemens.com/cax

#### **Tender specifications**

http://www.siemens.com/specifications