

Product type designation

RUGGEDCOM SFP1131-1FX50

RUGGEDCOM Accessory, SFP, 1 X 100MBIT/S, 100BASE-FX, LC-Interface, Optical: Single Mode Fiber Optic up to max. 50km, 1310nm, -40...+85 Degrees Celsius



Figure similar

Suitability for operation	compatible to RUGGEDCOM products with SFP-Slot
Interfaces	
Number of electrical/optical connections / for network components or terminal equipment / maximum	1
Number of optical interfaces / for network components or terminal equipment / maximum	1
Number of 100 Mbit/s LC ports	1
Design of the optical interface / for network components or terminal equipment	LC
Range / at the optical interface / depending on the optical fiber used	50 km
Ambient conditions	
Ambient temperature	
• during operation	-40 ... +85 °C
• during storage	-40 ... +85 °C
• during transport	-40 ... +85 °C

- Note

A maximum operating temperature of +85 °C is permissible for a duration of 16 hours

Relative humidity / at 25 °C / without condensation / during operation / maximum

95 %

Design, dimensions and weights

Design	SFP Module
Width	14 mm
Height	9 mm
Depth	57 mm
Net weight	0.01 kg
Product feature / conformal coating	No
Mounting type	latched

Standards, specifications, approvals

Standard	<ul style="list-style-type: none"> for safety / from CSA and UL for emitted interference for interference immunity 	<p>UL 60950-1, CSA C22.2 No. 60950-7</p> <p>EN 61000-6-4 (Class A)</p> <p>EN 61000-6-2</p>
Laser protection class		Complies with 21 CFR chapter 1, subchapter J
Certificate of suitability	<ul style="list-style-type: none"> CE marking C-Tick KC approval E1 approval IEC 61850-3 	<p>EN 61000-6-2, EN 61000-6-10</p> <p>Yes</p> <p>No</p> <p>No</p> <p>No</p> <p>Yes</p>

Further information / Internet-Links

Internet-Link	<ul style="list-style-type: none"> to website: Industry Mall/RUGGEDCOM selector to website: Siemens RUGGEDCOM to website: Selector for cables and connectors to website: Industrial communication to website: Industry Mall to website: Information and Download Center to website: Image database to website: CAx Download Manager to website: Industry Online Support 	<p>http://ruggedcom-selector.automation.siemens.com</p> <p>http://siemens.com/ruggedcom</p> <p>http://www.siemens.com/snst</p> <p>http://www.siemens.com/simatic-net</p> <p>https://mall.industry.siemens.com</p> <p>http://www.siemens.com/industry/infocenter</p> <p>http://automation.siemens.com/bilddb</p> <p>http://www.siemens.com/cax</p> <p>https://support.industry.siemens.com</p>
---------------	--	--

last modified:

12/16/2019