

SINAMICS/ SIMOVERT MASTERDRIVES BRAKING RESISTOR
675-780V DC 100 kW, 6.2 OHM



Figure similar

Order number	
Phase number / of the input voltage	Wert fehlt!
Type of voltage / of the input voltage	Wert fehlt!
Input voltage	Wert fehlt! ... Wert fehlt!
Consumed active power / rated value	25 kW
• maximum	150 kW
Input voltage / of the temperature switch / at AC / maximum	Wert fehlt!
Electrical resistance / of the braking resistor	6.2 Ω
Width	740 mm
Height	605 mm
Depth	485 mm
Net weight	43 kg

Further information

Information und Download Center

https://www.automation.siemens.com/mcms/infocenter/content/en/Pages/order_form.aspx

Technical documentation

<http://w3.siemens.com/mcms/mc-solutions/en/motion-control/support/technical-documentation/Pages/technical-documentation.aspx>

Industry Mall

<https://eb.automation.siemens.com/mall/en/WW/Cataog/Product/6SE7031-3FS87-2DC0/all>

Industry Online Support

<http://support.automation.siemens.com/WW/view/en/6SE7031-3FS87-2DC0/all>