

SCM-I QV P**Weidmüller Interface GmbH & Co. KG**

Klingenbergstraße 26

D-32758 Detmold

Germany

www.weidmueller.com**Product image**

Cross-connection for the sockets in the RIDERSERIES
RCM

General ordering data

Version	RIDERSERIES RCM, Cross-connector
Order No.	8870850000
Type	SCM-I QV P
GTIN (EAN)	4032248631698
Qty.	10 pc(s).

SCM-I QV P

Weidmüller Interface GmbH & Co. KG

Klingenbergstraße 26

D-32758 Detmold

Germany

www.weidmueller.com

Technical data

Dimensions and weights

Net weight	1.2 g	Width	28 mm
Width (inches)	1.102 inch		

Temperatures

Storage temperature	-40 °C...85 °C	Operating temperature	-45 °C...70 °C
Humidity	40 °C / 93 % rel. humidity, no condensation		

Cross-connection data

Rated current	12 A	Insulation	Yes
Touch-safe protection	Yes	Colour	white
Number of cross-connected terminals	2	Pitch in mm (P)	25.5 mm
Type of mounting	Plugged		

General data

Colour	white
--------	-------

Connection data

Pitch in mm (P)	25.5 mm
-----------------	---------

Classifications

ETIM 6.0	EC002586	ETIM 7.0	EC002586
ECLASS 9.1	27-37-16-92	ECLASS 10.0	27-37-16-92
ECLASS 11.0	27-37-16-92		

Approvals

Approvals



ROHS	Conform
------	---------

Downloads

Engineering Data	STEP
Engineering Data	EPLAN, WSCAD

SCM-I QV P


Weidmüller Interface GmbH & Co. KG
Klingenbergstraße 26
D-32758 Detmold
Germany

www.weidmueller.com

Drawings

Example of use


How to install cross connection



Plug cross connection direct
into wire-connection opening

Plug the cross-connection in the cable connections

Example of use



Cross connection:
SCM-I QV P
Part-No. 8870850000

Sockets:
SCM-I xCO P

Cross-connector bridges to the same
connection on the neighbouring base