

Inductive conductivity transmitter



Main features

- Range from 500 µS/cm to 1000 mS/cm
- All hygienic design
- Built in graphical display CombiView DFON
- Very fast temperature compensation
- Easy and full programmable with FlexProgrammer 9701
- AFI5 split version with remote

sensor

- Separate 4...20 mA output for conductivity / concentration and 4...20 mA output for temperature
- FDT software
- 3-A approved
- EHEDG
- Touch screen

Applications

- Controlling CIP procedure
- Controlling filling machines

Electrical specifications

- Detection of specific medias
- Water systems with >50 µS/cm

Technical spec	cifications		
Housing material		FlexHousing, Ø80 mm Stainless steel, AISI 304	1
Cable (AFI5)		2.5 / 5.0 / 10.0 meter	
	Material	PUR	
	Temperature	-4080°C	
Process connection	on	G1A hygienic, rotating (for other connections so ters page 4)	ee adap-
Insertion length	Standard Medium Long	37 mm / hygienic version 41 mm 60 mm / hygienic version 64 mm 83 mm / hygienic version 87 mm	
Material	Not wetted Wetted parts	Stainless steel AISI 304 PEEK natura, unfilled	
Surface	Wetted parts	Ra < 0.8 μm	
Measuring range	Conductivity	0 500 μS/cm 0 10 14 selectable ranges	000 mS/cm
	Concentration	4 factory set media/range 1 customer defined media	
	Temperature	-30 150°C Free programmable range	е
Accuracy (sensor incl. transmitter @ 25°C ambient)	Cond./conc.	$\begin{array}{c} 0 \; \; 500 \; \mu \text{S/cm} \\ 0 \; \; 1 \; / \; 0 \; \; 500 \; \text{mS/cm} \\ 0 \; \; 1000 \; \text{mS/cm} \end{array}$	≤ 1.5 % ≤ 1.0 % ≤ 1.5 %
	Temperature	≤ 0.4°C	
Temperature compensation		0.0 5.0% / K, free adj	ustable
Compensation ran	ige	-20 150°C	
Reference temperature		25°C (adjustable)	
Sampling time		< 0.3 second	
Response time	Cond./conc.	t ₉₀ < 2.0 seconds	
	Temperature	t ₉₀ < 15 seconds	
Start up time without	out display	≤ 10 seconds	
Start up time with display		≤ 15 seconds	

Power supply		15 35 VDC	
Output	Cond./conc.	4 20 mA 4 20 mA + HART®	
	Temperature	4 20 mA	
	Relays	2 relays included in the display	
Display (for more information please see page 3)		Without display With DFON display, 2 relay-output galvanic separated	
Temperature drift	Conductivity	≤ 0.1%/K ^{1) 2)}	
	Temperature	\leq 0.5%/K $^{1)}$ AFI5: \leq 0.5%/K + 0.005%/K pr. m sensor cable	
El. connection	Left side	M12, 4-pin M16 or M20 cable gland	
	Right side	M12, 4-pin (4 20 mA output only) M12, 8-pin (4 20 mA + relay output) M16 or M20 cable gland	
Material		Plastic (PA) Stainless steel	
General specifications			
Media temperature	9	-20 140°C 150°C up to 1 hour	
Media pressure		< 25 bar (helium tested)	

General spe	ecifications	
Media temper	ature	-20 140°C 150°C up to 1 hour
Media pressu	re	< 25 bar (helium tested)
Ambient temperature	Without display With display	-40 85°C -30 80°C
Isolation volta	ige	500 VAC
Protection class	EN60529/A2:2013	IP67 / IP69K
Humidity	IEC 68.2.38	98% condensing
Vibrations		IEC 60068.2.6 - test Fc 1.0 mm (2-13.2 hz) 0.7g (13.2-100 hz)

¹⁾ Factor of change in process temperature from 25°C

²⁾ Range 0...500 µS/cm ≤0.3%/K



Inductive conductivity transmitter

Conductivity ranges (selectable)

 $0\,...\,500~\mu\text{S/cm}$

0 ... 1 mS/cm 0 ... 10 mS/cm 0 ... 100 mS/cm 1000 mS/cm

0 ... 5 mS/cm 0 ... 50 mS/cm 0 ... 500 mS/cm

Definition:

 $1000 \mu S/cm = 1 mS/cm$ 1000 mS/cm = 1 S/cm

Conductivity in different media:

Conduc	ctivity		Media group	Media
55 r	nS/cm		Water	Ultra-pure water
1 μ	μS/cm			Pure water
10 µ	μS/cm			Process water
600 j	μS/cm		Food	Drinking water
				Beer
1 r	mS/cm			Milk
		AFIX		Orange juice
10 r	mS/cm	range		Apple juice
100 r	mS/cm		Process	Phosphoric acid
				Hydrochloric acid
1000 r	mS/cm			Sodium hydroxide

Concentration ranges (selectable)

NaOH (caustic soda) 0 ... 15% by weight (0 ... 90°C)

25 ... 50% by weight (0 ... 90°C)

 HNO_3 (nitric acid) 0 ... 25% by weight (0 ... 80°C)

36 ... 82% by weight (0 ... 80°C)

1 x customer defined (30 point linearization)

Compliance and approvals		
Apply to	EU directives FDA	10/2011, 1935/2004, 2023/2006 PEEK : CFR 21.177.2415
Approvals		3-A
		EHEDG
		cULus listed, E491206
		IEC 61010-1:2010
		IEC 61010-2-201:2013

Display

Input	
Input from AFIx transmitter	Digital, 2-way for communication between transmitter and display
Accuracy	\leq ± 0.1% of input from AFIx ambient -10 70°C \leq ± 0.2% of input span ambient -3010 / 7080°C
Update time	≤ 1 second. Typical 0.3 second

User-config	uirob	0.010
USEI =COIIII		le uala

User defined unit

Error/warning indication	Individually configurable display and backlight indication in white, green or red colour, steady or flashing light. Configurable limits over the range.
Media description	Customer programmable e.g. " MILK " " Water " " NaOH "
Measuring unit	µS/cm, mS/cm %

8 x 20 pixel matrix

Relay		
Contacts	2 x solid state relays	
Load current	Max. 75 mA	
Voltage	Max. 60 V _p	
Display		
Туре	FSTN Graphical LCD	
Display range	-999999999	

туре	FSTN Graphical LCD
Display range	-999999999
Digit height	Max. 22 mm
Temperature drift	≤ 0.0001%/K inside optimal range -10 70°C ≤ 0.00015%/K outside optimal range -3010 / 7080°C

Environmental conditions


Optimal readability	-10 70°C	
Operating temperature	-30 80°C	

Mechanical data	
Material	Polycarbonate
Protection class	IP67/IP69K

EN/2019-06-04 Design and specifications subject to change without notice



Inductive conductivity transmitter



Visual alert



White background



Green background



Red background




Error message and red background

Working principle

The measuring cell is a homogeneous sealed body all in PEEK. Through the body is a hole, through which the media flows. Built-in around the hole are two coils; a primary coil supplied with an AC voltage and a secondary coil, which picks up a small signal through the media induced voltage. The size of this voltage is dependent on the conductivity of the media. This signal is amplified and handled in the electronics to a linear analogue 4...20 mA output signal. Also built into the body is a Pt100 sensor placed in the tip of the sensor. This is measuring the media temperature to enable temperature compensation of the conductivity signal, which is very temperature dependent. The Pt100 sensor signal is also available as an analogue 4...20 mA output signal.

The coils and sensor are encapsulated in the PEEK sensor body, with surface roughness (Ra) <0.8 μ m. It is therefore well suited for use in hygienic processes or direct in concentrated acids or alkalis.




EN/2019-06-04 Design and specifications subject to change without notice




Inductive conductivity transmitter

Dimensions in mm AFI4


Front view



Bottom connection



Rear connection



Short version 37 mm

Standard Hygienic


Hygienic

Medium version 60 mm

Standard Hygienic Hygienic

Long version 83 mm

Standard Hygienic Hygienic







The sensor is 3-A approved when mounted in one of the 3-A approved G1A mounting adapters below.

The sensor is EHEDG approved when mounted in one of the EHEDG approved G1A mounting adapters below.

G1" mounting adapters

Welding connection



ZPW2-521





ISO 2852 DN38 ISO 2852 DN51



ZPH1-5213 ZPH1-5216



DIN 11851 DN32 **ZPH3-5222** DIN 11851 DN40 ZPH3-5224 DIN 11851 DN50 ZPH3-5225 DIN 11851 DN65 ZPH3-5227



Threaded connections



DIN 11864-1-A DN40 ZPH3-5254 DIN 11864-1-A DN50 **ZPH3-5255**

Union nut



ZPX4-xx0

For pipe



DN 40...50 DN 60...150

www.baumer.com

ZPW2-526 ZPW2-527



ZPH1-524E Variline, type N

SMS 1145 DN 38 ZPH1-5233 SMS 1145 DN 51 ZPH1-5236

Data sheet AFI4 / AFI5 Page 4 / 7




Inductive conductivity transmitter

Dimensions AFI5

Wall mounted version Pipe mounted version Side view Front view Front view Side view PCO Ø 95 Ø 91

AFI5 cable sensor Hole diameter Ø6.45





The sensor is 3-A approved when mounted in one of the 3-A approved G1A mounting adapters, shown on page 4.



The sensor is EHEDG approved when mounted in one of the EHEDG approved G1A mounting adapters, shown on page 4.


EN/2019-06-04 Design and specifications subject to change without notice



Inductive conductivity transmitter

Electrical connection

Left side electrical connection (Front view)



Left side M12, 4 pin connector

1. Brown	Supply (+)	(1535 vdc)
2. White	Cond. (-)	(420 mA)
3. Blue	Supply (-)	(1535 vdc)
4. Black	Cond. (+)	(420 mA)

Note:

If a M12 4-pin connector for left and right side is selected the AFI4 is directly compatible with the previous Baumer ISL conductivity transmitter.

To connect the FlexProgrammer to the transmitter

Com 1 Red clip Com 2 Black clip

The data entered to the transmitter will automatically be displayed on the DFON display via the ribbon cable (UnitCom)

To connect the FlexProgrammer to the DFON display


Com 1 Red clip Com 2 Black clip

Colour change, relay set-points and error messages etc. can be setup be set in the DFON display.

To set the external input for range selection


Range	S1	S2	Range	S1	S2
1	N.C.	N.C.	3	N.C.	24 VDC
2	24 VDC	N.C.	4	24 VDC	24 VDC

Electrical connection on the AFIx transmitter



The ground connection () is to be connected with the cable shield if using cable gland and shielded cable.

Right side electrical connection (Front view)




Right side M12, 4-pin connector

1. Brown	S1	(external input)
2. White	Temp. (-)	(420 mA)
3. Blue	S2	(external input)
4. Black	Temp. (+)	(420 mA)

Note:

The pin 2 in left connection and pin 2 in right connection can be connected as common - for both Con. and Temp. 4...20 mA output.

Right side electrical connection with relay output



Right side M12, 8 pin connector


1. White 2. Brown 3. Green	S1 Temp. (+) Relay 2	(external input) (420 mA)
4. Yellow	Relay 2	
5. Grey	Relay 1	
6. Light red	Relay 1	
7. Blue	Temp. (-)	(420 mA)
8. Red	S2	(external input)

The pin 2 in left connection and pin 7 in right connection can be connected as common - for both Con. and Temp. 4...20 mA output.

Electrical connection on the display with relay output


1. Not connected 2. Not connected

3. Green	Relay 2
4. Yellow	Relay 2
5. Grey	Relay 1
6. Light red	Relay 1
(3 + 5 can be	connected
common)	





Inductive conductivity transmitter



Page 7 / 7