Product datasheet Characteristics

LA1LC071B

TeSys Integral - shunt trip - 24 V AC 50/60 Hz - without time delay



Main

TeSys	=
LA1LC	
Shunt trip	
LD4 LD5	
Control	
TeSys Integral contactor breaker	
	LA1LC Shunt trip LD4 LD5 Control

Complementary

Complementary		<u> </u>
[Uc] control circuit voltage	24 V AC 50/60 Hz	<u> </u>
Time delay	Without time delay	
Voltage release type	Shunt trip Instantaneous	o c
Control circuit voltage limits	0.71.1 Uc	
Threshold tripping voltage	0.350.7 Uc	
Inrush power in VA	8 VA AC	
Hold-in power consumption in VA	4 VA AC	9
Operating time	>= 10 ms	
Connections - terminals	Screw connection	9.
Quantity per set	Set of 10	
Product weight	0.15 kg	<u>.</u>

Offer Sustainability

REACh Regulation	REACh Declaration	
REACh free of SVHC	Yes	
EU RoHS Directive	Compliant EU RoHS Declaration	
Toxic heavy metal free	Yes	
Mercury free	Yes	
RoHS exemption information	Yes	
China RoHS Regulation	China RoHS declaration	

Life Is On Schneider

WEEE	The product must be disposed on European Union markets following specific waste collection and never end up in rubbish bins	
Contractual warranty		
Warranty	18 months	