




Plug connectors and cables
Plug connectors and cables / Connecting cable
(female connector-open)

DOL-0J08-G03MAA3



Plug connectors and cables
Plug connectors and cables / Connecting cable (female connector-open)

Model Name > [DOL-0J08-G03MAA3](#)
Part No. > [2046875](#)



Technical data

Accessory group:	Plug connectors and cables
Accessory family:	Connecting cables with female connector
Connection type head A:	Female connector, JST, 8-pin, straight
Connection type head B:	Cable
Cable diameter:	Ø 5.6 mm
Conductor cross-section:	4 x 2 x 0.15 mm ²
Shielding:	Shielded
Bending radius:	> 7.5 x Leitungsdurchmesser im Schleppbetrieb, > 5 x Leitungsdurchmesser bei fester Verlegung
LED indicator:	-
Special feature:	Drag chain use
Signal type:	Incremental
Items supplied:	JST including sealing
Cable:	3 m, 8-pole
Jacket material:	PUR halogen-free
Jacket color:	Black

PIN assignment

PIN	Signal TTL, HTL	Signal sine 1.0 V _{ss}	Color of wires
1	$\overline{B}$	SIN-	Black
2	Not connected	Not connected	
3	Z	Z	Lilac
4	$\overline{Z}$	$\overline{Z}$	Yellow
5	A	COS+	White
6	$\overline{A}$	COS-	Brown
7	Not connected	Not connected	
8	B	SIN+	Pink
9	Not connected	Not connected	
10	GND	GND	Blue
11	Not connected	Not connected	
12	U _s	U _s	Red
Shield	Shield ¹⁾	Shield ²⁾	

Attention!
The flexible wires twisted in pairs must be assigned in accordance with the signals.
White/Brown = A/ $\overline{A}$ oder COS+/COS-
Lilac/Yellow = Z/ $\overline{Z}$
Pink/Black = B/ $\overline{B}$ oder SIN+/SIN-
Red/Blue = preferably U_s and GND

¹⁾ Shield connected to housing on side of encoder, connected to ground on side of control.
Attention! In combination with the electrical interfaces A, C, E and P only.

Australia

Phone +61 3 9457 0600
1800 33 48 02 – tollfree
E-Mail sales@sick.com.au

Belgium/Luxembourg

Phone +32 (0)2 466 55 66
E-Mail info@sick.be

Brasil

Phone +55 11 3215-4900
E-Mail marketing@sick.com.br

Canada

Phone +1 905 771 14 44
E-Mail information@sick.com

Česká republika

Phone +420 2 57 91 18 50
E-Mail sick@sick.cz

China

Phone +86 4000 121 000
E-Mail info.china@sick.net.cn
Phone +852-2153 6300
E-Mail ghk@sick.com.hk

Danmark

Phone +45 45 82 64 00
E-Mail sick@sick.dk

Deutschland

Phone +49 211 5301-301
E-Mail info@sick.de

España

Phone +34 93 480 31 00
E-Mail info@sick.es

France

Phone +33 1 64 62 35 00
E-Mail info@sick.fr

Great Britain

Phone +44 (0)1727 831121
E-Mail info@sick.co.uk

India

Phone +91-22-4033 8333
E-Mail info@sick-india.com

Israel

Phone +972-4-6881000
E-Mail info@sick-sensors.com

Italia

Phone +39 02 27 43 41
E-Mail info@sick.it

Japan

Phone +81 (0)3 5309 2112
E-Mail support@sick.jp

Magyarország

Phone +36 1 371 2680
E-Mail office@sick.hu

Nederland

Phone +31 (0)30 229 25 44
E-Mail info@sick.nl

Norge

Phone +47 67 81 50 00
E-Mail sick@sick.no

Österreich

Phone +43 (0)22 36 62 28 8-0
E-Mail office@sick.at

Polska

Phone +48 22 837 40 50
E-Mail info@sick.pl

România

Phone +40 356 171 120
E-Mail office@sick.ro

Russia

Phone +7-495-775-05-30
E-Mail info@sick.ru

Schweiz

Phone +41 41 619 29 39
E-Mail contact@sick.ch

Singapore

Phone +65 6744 3732
E-Mail sales.gsg@sick.com

Slovenija

Phone +386 (0)1-47 69 990
E-Mail office@sick.si

South Africa

Phone +27 11 472 3733
E-Mail info@sickautomation.co.za

South Korea

Phone +82 2 786 6321/4
E-Mail info@sickkorea.net

Suomi

Phone +358-9-25 15 800
E-Mail sick@sick.fi

Sverige

Phone +46 10 110 10 00
E-Mail info@sick.se

Taiwan

Phone +886 2 2375-6288
E-Mail sales@sick.com.tw

Türkiye

Phone +90 (216) 528 50 00
E-Mail info@sick.com.tr

United Arab Emirates

Phone +971 (0) 4 88 65 878
E-Mail info@sick.ae

USA/México

Phone +1(952) 941-6780
1 (800) 325-7425 – tollfree
E-Mail info@sickusa.com

More representatives and agencies
at www.sick.com