



Main

Range of product	Preventa Safety detection
Accessory / separate part category	Protection accessories
Accessory / separate part type	Protective cover
Accessory / separate part designation	Lexan protective covers for transmitter-receiver pair
Product compatibility	XUSLB...2120 XUSLDM...2120
Accessory / separate part destination	Safety light curtain type 4
Height	2150 mm
Quantity per set	Set of 2

Complementary

Material	Lexan
Sensing distance reduction coefficient	0.91 Sn
Product weight	1935 kg

Environment

Resistance to chemical agents	<p>Acids</p> <p>Aliphatic hydrocarbons</p> <p>Limited resistant against alcohols</p> <p>Limited resistant against alkalis</p> <p>Limited resistant against greases and oil</p> <p>Limited resistant against detergents and cleaners</p> <p>Not resistant against amines</p> <p>Not resistant against esters</p> <p>Not resistant against ketones</p> <p>Not resistant against aromatic hydrocarbons</p> <p>Not resistant against halogenated hydrocarbons</p> <p>Not resistant against detergents and cleaners containing alkaline products</p> <p>Not resistant against silicone oils and greases containing alkaline products</p> <p>Limited resistant against silicone oils and greases without alkaline products</p>
Ambient air temperature for operation	0...55 °C
Ambient air temperature for storage	-25...70 °C

Offer Sustainability

Sustainable offer status	Not Green Premium product
RoHS (date code: YYWW)	Compliant - since 1102 - Schneider Electric declaration of conformity

The information provided in this documentation contains general descriptions and/or technical characteristics of the products contained herein. This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications. It is the duty of any such user or integrator to perform the appropriate and complete risk analysis, evaluation and testing of the products with respect to the relevant specific application or use thereof. Neither Schneider Electric Industries SAS nor any of its affiliates or subsidiaries shall be responsible or liable for misuse of the information contained herein.